

**Rockchip
RK3228B
Datasheet**

**Revision 1.3
Sep. 2016**

Revision History

Date	Revision	Description
2016-9-1	1.3	Update
2016-4-6	1.2	Updated with RK3228B-D related info.
2015-12-8	1.1	Update
2015-12-4	1.0	Initial Release

Rockchip Confidential

Table of Content

Table of Content	3
Figure Index	4
Table Index.....	5
Warranty Disclaimer.....	6
Chapter 1 Introduction	7
1.1 Overview	7
1.2 Features	7
1.3 Block Diagram	16
Chapter 2 Package Information.....	17
2.1 Order Information	17
2.2 Top Marking	17
2.3 Dimension.....	18
2.4 Ball Map	21
2.5 Pin Number Order	28
2.6 RK3228B Power/Ground IO Description	38
2.7 RK3228B Function IO Description	40
2.8 IO Pin Name Description	45
2.9 RK3228B IO Type.....	49
Chapter 3 Electrical Specification	50
3.1 Absolute Maximum Ratings.....	50
3.2 Recommended Operating Condition	50
3.3 DC Characteristics	51
3.4 Electrical Characteristics for General IO	53
3.5 Electrical Characteristics for PLL	53
3.6 Electrical Characteristics for USB Interface.....	54
3.7 Electrical Characteristics for DDR IO.....	55
3.8 Electrical Characteristics for eFuse	55
3.9 Electrical Characteristics for HDMI	55
3.10 Electrical Characteristics for VDAC	56
3.11 Electrical Characteristics for TSADC.....	56
Chapter 4 Thermal Management.....	57
4.1 Overview	57
4.2 Package Thermal Characteristics	57

Figure Index

Fig.1-1 RK3228B Block Diagram	16
Fig.2-1 RK3228BBGA316 Package Top View and bottom view.....	19
Fig.2-2 RK3228B BGA316 Package Side View.....	19
Fig.2-3 RK3228BBGA316 Package Dimension	19
Fig.2-4 RK3228B BGA400 Package Top View and bottom view.....	20
Fig.2-5 RK3228B BGA400 Package Side View.....	20
Fig.2-6 RK3228B BGA316 Package Dimension.....	21
Fig.2-7 RK3228BBGA316Ball Map	24
Fig.2-8 RK3228BBGA400Ball Map	28

Rockchip Confidential

Table Index

Table 2-1RK3228B BGA316 Pin Number Order Information 28

Table 2-2 RK3228B BGA400 Pin Number Order Information 32

Table 2-3 RK3228B Power/Ground IO information forBGA316..... 38

Table 2-4 RK3228B function IO description 40

Table 2-5 RK3228B IO function description list..... 45

Table 2-6 RK3228B IO Type List..... 49

Table 3-1 RK3228B absolute maximum ratings 50

Table 3-2 RK3228B recommended operating condition 50

Table 3-3 RK3228B DC Characteristics 51

Table 3-4 RK3228B Electrical Characteristics for Digital General IO 53

Table 3-5 RK3228B Electrical Characteristics for PLL 53

Table 3-6 RK3228B Electrical Characteristics for USB Interface..... 54

Table 3-7 RK3228B Electrical Characteristics for DDR IO..... 55

Table 3-8 RK3228B Electrical Characteristics for eFuse 55

Table 3-9 RK3228B Electrical Characteristics for HDMI 55

Table 3-10 RK3228B Electrical Characteristics for VDAC 56

Table 3-11 RK3228B Electrical Characteristics for TSADC..... 56

Table 4-1 RK3228B Thermal Resistance Characteristics 57

Rockchip Confidential

Warranty Disclaimer

Rockchip Electronics Co.,Ltd makes no warranty, representation or guarantee (expressed, implied, statutory, or otherwise) by or with respect to anything in this document, and shall not be liable for any implied warranties of non-infringement, merchantability or fitness for a particular purpose or for any indirect, special or consequential damages.

Information furnished is believed to be accurate and reliable. However, Rockchip Electronics Co.,Ltd assumes no responsibility for the consequences of use of such information or for any infringement of patents or other rights of third parties that may result from its use.

Rockchip Electronics Co.,Ltd's products are not designed, intended, or authorized for using as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Rockchip Electronics Co.,Ltd's product could create a situation where personal injury or death may occur, should buyer purchase or use Rockchip Electronics Co.,Ltd's products for any such unintended or unauthorized application, buyers shall indemnify and hold Rockchip Electronics Co.,Ltd and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, expenses, and reasonable attorney fees arising out of, either directly or indirectly, any claim of personal injury or death that may be associated with such unintended or unauthorized use, even if such claim alleges that Rockchip Electronics Co.,Ltd was negligent regarding the design or manufacture of the part.

Copyright and Patent Right

Information in this document is provided solely to enable system and software implementers to use Rockchip Electronics Co.,Ltd's products. There are no expressed or implied copyright and patent licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Rockchip Electronics Co.,Ltd does not convey any license under its patent rights nor the rights of others.

All copyright and patent rights referenced in this document belong to their respective owners and shall be subject to corresponding copyright and patent licensing requirements.

Trademarks

Rockchip and Rockchip logo and the name of Rockchip Electronics Co.,Ltd's products are trademarks of Rockchip Electronics Co.,Ltd. and are exclusively owned by Rockchip Electronics Co.,Ltd. References to other companies and their products use trademarks owned by the respective companies and are for reference purpose only.

Confidentiality

The information contained herein (including any attachments) is confidential. The recipient hereby acknowledges the confidentiality of this document, and except for the specific purpose, this document shall not be disclosed to any third party.

Reverse engineering or disassembly is prohibited.

ROCKCHIP ELECTRONICS CO.,LTD. RESERVES THE RIGHT TO MAKE CHANGES IN ITS PRODUCTS OR PRODUCT SPECIFICATIONS WITH THE INTENT TO IMPROVE FUNCTION OR DESIGN AT ANY TIME AND WITHOUT NOTICE AND IS NOT REQUIRED TO UPDATE THIS DOCUMENTATION TO REFLECT SUCH CHANGES.

Copyright © 2016 Rockchip Electronics Co., Ltd.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted in any form or by any means, electric or mechanical, by photocopying, recording, or otherwise, without the prior written consent of Rockchip Electronics Co.,Ltd.

Chapter 1 Introduction

1.1 Overview

RK3228B is a high performance Quad-core application processor for smart TV-Box. Especially it is a high-integration and cost efficient SOC for 4K10-bit H.265/H.264 TV-Box.

Quad-core Cortex-A7 is integrates with separately Neon and FPU coprocessor, also shared 256KB L2 Cache. The penta-core GPU including one geometry processors (GP) and dual pixel processors (PP) and dual core RK Enhanced Graphic Processor, support smoothly high-resolution display and mainstream game.

Lots of high-performance interface to get very flexible solution, such as multi-pipe display with HDMI2.0, TV Encoder is integrated for support security BOOT. 32bits DDR3/LPDDR3 provides high memory bandwidths for high-performance.

Lots of high-performance interface to get very flexible solution, such as multi-pipe display with HDMI2.0, TV Encoder is integrated for support security BOOT. 32bits DDR3/LPDDR3 provides high memory bandwidths for high-performance.

RK3228B-D support Dolby™ audio decode and transfer to HDMI, SPDIF or I2S, also can output from audio DAC.

Remark: Dolby™ is a trademark of Dolby Laboratories.

1.2 Features

The features listed below which may or may not be present in actual product, may be subject to the third party licensing requirements. Please contact Rockchip for actual product feature configurations and licensing requirements.

1.2.1 Microprocessor

- Quad-core ARM Cortex-A7 MPCore processor, a high-performance, low-power and cached application processor
- Full implementation of the ARM architecture v7-A instruction set, ARM Neon Advanced SIMD (single instruction, multiple data) support for accelerated media and signal processing computation
- Separately Integrated Neon and FPU per CPU
- 32KB/32KB L1 I-Cache/D-Cache per CPU.
- Unified 256KB L2 Cache.

1.2.2 Memory Organization

- Internal on-chip memory
 - BootRom
 - Internal SRAM
- External off-chip memory[®]
 - DDR3/DDR3L/LPDDR2/LPDDR3
 - Async/Toggle/SyncNand Flash(include LBA Nand)

1.2.3 Internal Memory

- Internal BootRom
 - Size : 20KB
 - Support system boot from the following device :
 - ◆ 8bits AsyncNand Flash
 - ◆ 8bits toggle Nand Flash
 - ◆ SPI interface
 - ◆ eMMC interface
 - ◆ SDMMC interface
 - Support system code download by the following interface:

- ◆ USB OTG interface
- Internal SRAM
 - Size : 36KB

1.2.4 External Memory or Storage device

- Dynamic Memory Interface (DDR3/DDR3L/LPDDR2/LPDDR3)
 - Compatible with JEDEC standard
DDR3-1600/DDR3L-1600/LPDDR2-800/LPDDR3-1333 SDRAM
 - Supports 32 bits data width, 2 ranks (chip selects), totally 2GB(max) address space.
 - Programmable timing parameters to support DDR3/DDR3L/LPDDR2/LPDDR3 SDRAM from various vendor
 - Advanced command reordering and scheduling to maximize bus utilization
 - Low power modes, such as power-down and self-refresh for DDR3/LPDDR2/LPDDR3 SDRAM; clock stop and deep power-down for LPDDR2 SDRAM
 - Compensation for board delays and variable latencies through programmable pipelines
 - Programmable output and ODT impedance with dynamic PVT compensation
- Nand Flash Interface
 - Support 8bits async/toggle/sync nandflash, up to 4 banks
 - Support LBA nandflash
 - 16bits, 24bits, 40bits, 60bits hardware ECC
 - For DDR nandflash, support DLL bypass and 1/4 or 1/8 clock adjust
 - For async/toggle nandflash, support configurable interface timing,
 - maximum data rate is 16bit/cycle
 - Embedded AHB master interface to do data transfer by DMA method
- eMMC Interface
 - Compatible with standard iNAND interface
 - Support MMC4.51 protocol
 - Provide eMMC boot sequence to receive boot data from external eMMC device
 - Support FIFO over-run and under-run prevention by stopping card clock automatically
 - Support CRC generation and error detection
 - Embedded clock frequency division control to provide programmable baud rate
 - Support block size from 1 to 65535Bytes
 - 8bits data bus width
- SD/MMC Interface
 - Compatible with SD3.0, MMC ver4.51
 - Support FIFO over-run and under-run prevention by stopping card clock automatically
 - Support CRC generation and error detection
 - Support block size from 1 to 65535Bytes
 - Data bus width is 4bits

1.2.5 System Component

- CRU (clock & reset unit)
 - Support clock gating control for individual components inside RK3228B
 - One oscillator with 24MHz clock input and 4 embedded PLLs
 - Support global soft-reset control for whole SOC, also individual soft-reset for every components
- Timer
 - 6 on-chip 64bits Timers in SoC with interrupt-based operation for non-secure application
 - 2 on-chip 64bits Timers in SoC with interrupt-based operation for secure application
 - Provide two operation modes: free-running and user-defined count

- Support timer work state checkable
- Fixed 24MHz clock input
- PWM
 - Four on-chip PWMs with interrupt-based operation
 - Programmable pre-scaled operation to bus clock and then further scaled
 - Embedded 32-bit timer/counter facility
 - Support capture mode
 - Support continuous mode or one-shot mode
 - Provides reference mode and output various duty-cycle waveform
- WatchDog
 - 32 bits watchdog counter width
 - Counter clock is from apb bus clock
 - Counter counts down from a preset value to 0 to indicate the occurrence of a timeout
 - WDT can perform two types of operations when timeout occurs:
 - ◆ Generate a system reset
 - ◆ First generate an interrupt and if this is not cleared by the service routine by the time a second timeout occurs then generate a system reset
 - Programmable reset pulse length
 - Totally 16 defined-ranges of main timeout period
- Bus Architecture
 - 128bit/64-bit/32-bit multi-layer AXI/AHB/APB composite bus architecture
 - 5 embedded AXI interconnect
 - ◆ CPU interconnect with four 64-bits AXI masters, one 64-bits AXI slaves, one 32-bits AHB master and lots of 32-bits AHB/APB slaves
 - ◆ PERI interconnect with two 64-bits AXI masters, one 64-bits AXI slave, five 32-bits AHB masters and lots of 32-bits AHB/APB slaves
 - ◆ Display interconnect with three 128-bits AXI master, four 64-bits AXI masters and one 32-bits AHB slave
 - ◆ GPU interconnect with one 128-bits AXI master with point-to-point AXI-lite architecture and 32-bits APB slave
 - ◆ VCODEC interconnect also with two 64-bits AXI master and two 32-bits AHB slave, they are point-to-point AXI-lite architecture
 - Flexible different QoS solution to improve the utility of bus bandwidth
- Interrupt Controller
 - Support 3 PPI interrupt source and 128 SPI interrupt sources input from different components inside RK3228B
 - Support 16 software-triggered interrupts
 - Input interrupt level is fixed , only high-level sensitive
 - Two interrupt outputs (nFIQ and nIRQ) separately for each Cortex-A7, both are low-level sensitive
 - Support different interrupt priority for each interrupt source, and they are always software-programmable
- DMAC
 - Micro-code programming based DMA
 - The specific instruction set provides flexibility for programming DMA transfers
 - Linked list DMA function is supported to complete scatter-gather transfer
 - Support internal instruction cache
 - Embedded DMA manager thread
 - Support data transfer types with memory-to-memory, memory-to-peripheral, peripheral-to-memory
 - Signals the occurrence of various DMA events using the interrupt output signals
 - Mapping relationship between each channel and different interrupt outputs is

- software-programmable
- One embedded DMA controller for system
- DMAC features:
 - ◆ 8 channels totally
 - ◆ 16 hardware request from peripherals
 - ◆ 2 interrupt output
 - ◆ Dual APB slave interface for register configuration, designated as secure and non-secure

1.2.6 Video CODEC

- Embedded memory management unit(MMU)
- Video Decoder
 - Real-time video decoder of MPEG-1, MPEG-2, MPEG-4,H.263, H.264, H.265,VC-1, VP8, MVC
 - MMU Embedded
 - Supports frame timeout interrupt , frame finish interrupt and bitstream error interrupt
 - Error detection and concealment support for all video formats
 - Output data format YUV420 semi-planar,YUV400(monochrome) ,YUV422 is supported by H.264
 - H.264 10bit up to HP level 5.1 : 2160P@60fps (4096x2304)
 - HEVC 10bit: 2160p @60fps(4096x2304)
 - MPEG-4 up to ASP level 5 : 1080p@60fps (1920x1088)
 - MPEG-2 up to MP : 1080p@60fps (1920x1088)
 - MPEG-1 up to MP : 1080p@60fps (1920x1088)
 - H.263 : 576p@60fps (720x576)
 - VC-1 up to AP level 3 : 1080p@30fps (1920x1088)
 - VP8 : 1080p@60fps (1920x1088)
 - MVC : 1080p@60fps (1920x1088)
 - For H.264, image cropping not supported
 - For MPEG-4, GMC(global motion compensation) not supported
 - For VC-1, upscaling and range mapping are supported in image post-processor
 - For MPEG-4 SP/H.263, using a modified H.264 in-loop filter to implement de-blocking filter in post-processor unit
- Video Encoder
 - Support video encoder for H.264 UP to HP@level4.1, MVC
 - Only support I and P slices, not B slices
 - Support error resilience based on constrained intra prediction and slices
 - Input data format:
 - ◆ YCbCr 4:2:0 planar
 - ◆ YCbCr 4:2:0 semi-planar
 - ◆ YCbYCr 4:2:2
 - ◆ CbYCrY 4:2:2 interleaved
 - ◆ RGB444 and BGR444
 - ◆ RGB555 and BGR555
 - ◆ RGB565 and BGR565
 - ◆ RGB888 and BRG888
 - ◆ RGB101010 and BRG101010
 - Image size is from 96x96 to 1920x1080(Full HD)
 - Maximum frame rate is up to 1920x1080 @ 30FPS®

1.2.7 JPEG CODEC

- JPEG decoder
 - Input JPEG file : YCbCr 4:0:0, 4:2:0, 4:2:2, 4:4:0, 4:1:1 and 4:4:4 sampling formats
 - Output raw image : YCbCr 4:0:0, 4:2:0, 4:2:2, 4:4:0, 4:1:1 and 4:4:4 semi-planar
 - Decoder size is from 48x48 to 8176x8176(66.8Mpixels)


- Support JPEG ROI(region of image) decode
- Maximum data rate[®] is up to 76million pixels per second
- Embedded memory management unit(MMU)

1.2.8 Image Enhancement (IEP module)

- Image format support
 - Input data: YUV420/YUV422
 - Output data: YUV420/YUV422
 - YUV swap
 - UV SP/P
 - BT601_l/BT601_f/BT709_l/BT709_f color space conversion
 - YUV up/down sampling
- De-interlace
 - 3x5 Y motion detection matrix
 - Source width up to 1920
 - Configured high frequency de-interlace
 - I4O2 (Input 4 field,output 2 frame) /I4O1B/I4O1T/I2O1B/I2O1T mode
- Interface
 - 32bit AHB bus slave
 - 64bit AXI bus master
 - Combined interrupt output

1.2.9 Graphics Engine

RK3228B’s GPU consists of penta-core that is tri-core 3D Graphics engine and dual-core RK Enhanced Graphic Processor.



- Tri-Core 3D Graphics Engine :
 - High performance OpenGL ES1.1 and 2.0, OpenVG1.1 etc.
 - Embedded 2 shader cores with shared hierarchical tiler
 - Separate vertex(geometry) and fragment(pixel) processing for maximum parallel throughput
 - Provide MMU and L2 Cache with 64KB size
- Dual-Core RK Enhanced Graphic Processor:
 - Source formats :
 - ◆ ABGR8888, XBGR888, ARGB8888, XRGB888
 - ◆ RGB888, RGB565
 - ◆ RGBA5551, RGBA4444
 - ◆ YUV420 planar, YUV420 semi-planar
 - ◆ YUV422 planar, YUV422 semi-planar

- ◆ YUV 10-bit for YUV420/422 semi-planar
- ◆ BPP8, BPP4, BPP2, BPP1
- Destination formats :
 - ◆ ABGR8888, XBGR888, ARGB8888, XRGB888
 - ◆ RGB888, RGB565
 - ◆ RGBA5551, RGBA4444
 - ◆ YUV420 planar, YUV420 semi-planar
 - ◆ YUV422 planar, YUV422 semi-planar
- Pixel Format conversion, BT.601/BT.709
- Max resolution: 8192x8192 source, 4096x4096 destination
- BitBLT
 - ◆ Two source BitBLT:
 - ◆ A+B=B only BitBLT, A support rotate&scale when B fixed
 - ◆ A+B=C second source (B) has same attribute with (C) plus rotation function
- Color fill with gradient fill, and pattern fill
- High-performance stretch and shrink
- Monochrome expansion for text rendering
- New comprehensive per-pixel alpha(color/alpha channel separately)
- Alpha blending modes including Java 2 Porter-Duff compositing blending rules , chroma key, pattern mask, fading
- Dither operation
- 0, 90, 180, 270 degree rotation
- x-mirror, y-mirror& rotation operation

1.2.10 Video OUT

- Display Interface
 - Support HDMI 2.0 output up to 4K@60Hz
 - TV Interface:TV encoder 10bit out for DAC
 - HDMI Interface : 24 bit(RGB888 YCbCr444),
30bit(RGB101010, YCbCr 420, YCbCr 444)
 - Max output resolution 4K for HDMI, 480i/576i for CVBS
 - 3 display layers :
 - ◆ Display layers of Win0, Win1, HWC
 - ◆ One background layer with programmable 24bits color
 - ◆ One video layer (win0/win1)
 - RGB888, ARGB888, RGB565, YCbCr422, YCbCr420, YCbCr444, YCbCr 420 10bit, YCbCr 422 10bit, YCbCr 444 10bit
 - maximum resolution is 4096x2304, support virtual display
 - 1/8 to 8 scaling up/down engine with arbitrary non-integer ratio
 - 256 level alpha blending(pre-multiplied alpha support)
 - Support transparency color key
 - Support BG, RG, RB swap, xy mirror
 - Support TV Encoder for PAL and NTSC
 - YCbCr2RGB(rec601-mpeg/rec601-jpeg/rec709)
 - YCbCr2RGB(BT2020)
 - RGB2YCbCr(BT601/BT709)
 - RGB2YCbCr(BT2020)
 - BT2020 and BT709/601 conversion
 - Win0 and Win1 layer overlay exchangeable
 - Support replication(16bits to 24bits) and dithering(24bits to 16bits/ 18bits) operation
 - Blank and blank display

1.2.11 HDMI

- Support YUV420 4k x 2k @ 60fps
- Support for 4k x 2k and 3D video formats
- Support for up to 10.2bps bandwidth

- HPD input analog comparator
- Compliant HDMI 2.0
- Compliance HDMI compliance Test specification 1.4
- Support HDCP 2.2
- Support multi-channels PCM or compressed audio transmission (32-192kHz Fs) from I2S/SPDIF, using IEC60958 and IEC 61937

1.2.12 Audio Interface

- I2S0/I2S1 with 8ch
 - I2S0/I2S1 supports up to 8 channels (8xTX or 8xRX)
 - Audio resolution from 16bits to 32bits
 - Sample rate up to 192KHz
 - Provides master and slave work mode, software configurable
 - Support 3 I2S formats (normal, left-justified, right-justified)
 - Support 4 PCM formats(early, late1, late2, late3)
 - I2S and PCM mode cannot be used at the same time
- I2S2/PCM with 2ch
 - Up to 2 channels (2xTX and 2xRX)
 - Audio resolution from 16bits to 32bits
 - Sample rate up to 192KHz
 - Provides master and slave work mode, software configurable
 - Support 3 I2S formats (normal, left-justified, right-justified)
 - Support 4 PCM formats(early, late1, late2, late3)
 - I2S and PCM cannot be used at the same time
- SPDIF
 - Support two 16-bit audio data store together in one 32-bit wide location
 - Support biphase format stereo audio data output
 - Support 16 to 31 bit audio data left or right justified in 32-bit wide sample data buffer
 - Support 16, 20, 24 bits audio data transfer in linear PCM mode
 - Support non-linear PCM transfer
 - Support multi-channels PCM or compressed audio transmission (32-192kHz Fs)
- Audio CODEC
 - 24bit DAC
 - Support Line-out
 - Support Mono, Stereo, 5.1 HiFi channel performance
 - Integrated digital interpolation and decimation filter.
 - Sampling rate of 8kHz/12kHz/16kHz/24kHz/32kHz/44.1KHz/48KHz/96KHz
 - Optional fractional PLL available that support 6MHz to 20MHz clock input to any clock

1.2.13 Connectivity

- SDIO interface
 - Compatible with SDIO 3.0 protocol
 - 4bits data bus widths
- TS interface
 - Supports one TS input channels.
 - Supports 4 TS Input Mode: sync/valid mode in the case of serial TS input; nosync/valid mode, sync/valid, sync/burst mode in the case of parallel TS input.
 - Supports 2 TS sources: demodulators and local memory.
 - Supports 2 Built-in PTIs(Programmable Transport Interface) to process TS simultaneously, and Each PTI supports:
 - ◆ 64 PID filters.
 - ◆ TS descrambling with 16 sets of Control Word under CSA v2.0 standard, up to

- 104Mbps
 - ◆ 16 PES/ES filters with PTS/DTS extraction and ES start code detection.
 - ◆ 4/8 PCR extraction channels
 - ◆ 64 Section filters with CRC check, and three interrupt mode: stop per unit, full-stop, recycle mode with version number check
 - ◆ PID done and error interrupts for each channel
 - ◆ PCR/DTS/PTS extraction interrupt for each channel
 - Supports 1 PVR(Personal Video Recording) output channel.
 - 1 built-in multi-channel DMA Controller.
- Smart Card
 - support cardactivationanddeactivation
 - supportcold/warmreset
 - supportAnswerToReset(ATR)responsereception
 - support T0 for asynchronoushalf-duplexcharactertransmission
 - support T1 for asynchronous half-duplexblocktransmission
 - support automatic operating voltage class selection
 - support adjustable clock rate and bit (baud) rate
 - support configurable automatic byte repetition
- GMAC 10/100/1000M Ethernet Controller
 - Supports 10/100/1000-Mbps data transfer rates with the RGMII interfaces
 - Supports 10/100-Mbps data transfer rates with the RMII interfaces
 - Supports both full-duplex and half-duplex operation
 - ◆ Supports CSMA/CD Protocol for half-duplex operation
 - ◆ Supports packet bursting and frame extension in 1000 Mbps half-duplex operation
 - ◆ Supports IEEE 802.3x flow control for full-duplex operation
 - ◆ Optional forwarding of received pause control frames to the user application in full-duplex operation
 - ◆ Back-pressure support for half-duplex operation
 - ◆ Automatic transmission of zero-quanta pause frame on deassertion of flow control input in full-duplex operation
 - Preamble and start-of-frame data (SFD) insertion in Transmit, and deletion in Receive paths
 - Automatic CRC and pad generation controllable on a per-frame basis
 - Options for Automatic Pad/CRC Stripping on receive frames
 - Programmable Inter-Frame-Gap (40-96 bit times in steps of 8)
 - Supports a variety of flexible address filtering modes
 - Separate 32-bit status returned for transmission and reception packets
 - Supports IEEE 802.1Q VLAN tag detection for reception frames
 - Support detection of LAN wake-up frames and AMD Magic Packet frames
 - Support checksum off-load for received IPv4 and TCP packets encapsulated by the Ethernet frame
 - Support checking IPv4 header checksum and TCP, UDP, or ICMP checksum encapsulated in IPv4 or IPv6 datagram
 - Comprehensive status reporting for normal operation and transfers with errors
 - Automatic generation of PAUSE frame control or backpressure signal to the GMAC core based on Receive FIFO-fill (threshold configurable) level
 - Handles automatic retransmission of Collision frames for transmission
 - Discards frames on late collision, excessive collisions, excessive deferral and under-run conditions
- Ethernet PHY
 - Integrated IEEE 802.3/802.3u compliant 10/100Mbps Ethernet PHY
 - Supporting both full and half duplex for either 10 or 100 Mb/s data rate
 - Auto MDIX capable

- Supports wake-on-LAN, EEE
- 100Base-FX support
- MII/RMII interface
- Supports auto-negotiation
- On-board diagnosis

- SPI Controller
 - Support serial-master and serial-slave mode, software-configurable
 - DMA-based or interrupt-based operation
 - Embedded two 32x16bits FIFO for TX and RX operation respectively
 - Support 2 chip-selects output in serial-master mode

- UART Controller
 - 3 on-chip UART controller inside RK3228B
 - DMA-based or interrupt-based operation
 - UART0/1/2 Embedded two 64Bytes FIFO for TX and RX operation respectively
 - Support 5bit,6bit,7bit,8bit serial data transmit or receive
 - Standard asynchronous communication bits such as start,stop and parity
 - Support different input clock for UART operation to get up to 4Mbps or other special baud rate
 - Support non-integer clock divides for baud clock generation
 - Support auto flow control mode

- I2C controller
 - 4 on-chip I2C controller in RK3228B
 - Multi-master I2C operation
 - Support 7bits and 10bits address mode
 - Software programmable clock frequency and transfer rate up to 400Kbit/s in the fast mode
 - Serial 8bits oriented and bidirectional data transfers can be made at up to 100Kbit/s in the standard mode

- GPIO
 - 4 groups of GPIO (GPIO0~GPIO3) , 32 GPIOs per group in GPIO0~GPIO3, totally have 128 GPIOs
 - All of GPIOs can be used to generate interrupt to Cortex-A7
 - All of pull-up GPIOs are software-programmable for pull-up resistor or not
 - All of pull-down GPIOs are software-programmable for pull-down resistor or not
 - All of GPIOs are always in input direction in default after power-on-reset

- USB Host2.0
 - Embedded 3 USB Host2.0 interfaces
 - Compatible with USB Host2.0 specification
 - Supports high-speed(480Mbps), full-speed(12Mbps) and low-speed(1.5Mbps) mode
 - Provides 16 host mode channels
 - Support periodic out channel in host mode

- USB OTG2.0
 - Compatible with USB OTG2.0 specification
 - Supports high-speed(480Mbps), full-speed(12Mbps) and low-speed(1.5Mbps) mode
 - Support up to 9 device mode endpoints in addition to control endpoint 0
 - Support up to 6 device mode IN endpoints including control endpoint 0
 - Endpoints 1/3/5/7 can be used only as data IN endpoint
 - Endpoints 2/4/6 can be used only as data OUT endpoint
 - Endpoints 8/9 can be used as data OUT and IN endpoint
 - Provides 9 host mode channels

1.2.14 Others

- Temperature Sensor(TS-ADC)
 - 10-bits SAR ADC up to 50KS/s sampling rate
 - 0~80C temperature range and 5C temperature resolution
- eFuse
 - Two high-density electrical Fuse is integrated: 256bits (32x8) / 1024bits (32x32)
 - Support standby mode
 - Provide inactive mode, VP must be 0V or Floating in this mode.
- Package Type
 - BGA316 (body: 14mm x 14mm ; ball size : 0.3mm ; ball pitch : 0.65mm)

Notes :

- ① DDR3/LPDDR2/LPDDR3 are not used simultaneously as well as async and sync ddrnand flash
- ② Actual maximum frame rate will depend on the clock frequency and system bus performance
- ③ Actual maximum data rate will depend on the clock frequency and JPEG compression rate

1.3 Block Diagram

The following diagram shows the basic block diagram for RK3228B.




Fig.1-1 RK3228B Block Diagram

Chapter 2 Package Information

2.1 Order Information

Orderable Device	RoHS status	Package	Package Qty	Device special feature
RK3228B	RoHS	TFBGA316	1190	4K Quad core processor
RK3228B2	RoHS	TFBGA400	700	4K Quad core processor
RK3228B-D	RoHS	TFBGA316	1190	4K Quad Core processor with Dolby audio support
RK3228B2-D	RoHS	TFBGA400	700	4K Quad Core processor with Dolby audio support

2.2 Top Marking



Rockchip: Brand Name

RKXXXXX: Chip Name

ABC: Subcontractor Code
XXXXXX: Die Lot NO#
DEFG: Date Code
 • The first pin



Rockchip: Brand Name

RKXXXXX: Chip Name

ABC: Subcontractor Code
XXXXXX: Die Lot NO#
DEFG: Date Code
 • The first pin



Rockchip: Brand Name

RKXXXXX: Chip Name

ABC: Subcontractor Code
XXXXXX: Die Lot NO#
DEFG: Date Code
 • The first pin





Rockchip: Brand Name

RKXXXXX: Chip Name

ABC: Subcontractor Code
XXXXXX: Die Lot NO#
DEFG: Date Code
 • The first pin

2.3 Dimension

2.3.1 BGA316 Dimension






Fig.2-1 RK3228BBGA316 Package Top View and bottom view




Fig.2-2 RK3228B BGA316 Package Side View

symbol	Dimension in mm			Dimension in inch		
	MIN	NOM	MAX	MIN	NOM	MAX
A	—	—	1.270	—	—	0.050
A1	0.160	0.210	0.260	0.006	0.008	0.010
A2	0.910	0.960	1.010	0.036	0.038	0.040
c	0.220	0.260	0.300	0.009	0.010	0.012
D	13.900	14.000	14.100	0.547	0.551	0.555
E	13.900	14.000	14.100	0.547	0.551	0.555
D1	—	12.350	—	—	0.486	—
E1	—	12.350	—	—	0.486	—
e	—	0.650	—	—	0.026	—
b	0.250	0.300	0.350	0.010	0.012	0.014
aaa	0.150			0.006		
bbb	0.200			0.008		
ddd	0.080			0.003		
eee	0.150			0.006		
fff	0.080			0.003		
N	316			316		
MD/ME	20/20			20/20		

Fig.2-3 RK3228BBGA316 Package Dimension

2.3.2 BGA400 Dimension




Fig.2-4 RK3228B BGA400 Package Top View and bottom view




Fig.2-5 RK3228B BGA400 Package Side View

Symbol	Dimension in mm			Dimension in inch		
	MIN	NOM	MAX	MIN	NOM	MAX
A	1.15	1.22	1.29	0.045	0.048	0.051
A1	0.21	0.26	0.31	0.008	0.010	0.012
A2	0.91	0.96	1.01	0.036	0.038	0.040
c	0.22	0.26	0.30	0.009	0.010	0.012
D	18.90	19.00	19.10	0.744	0.748	0.752
E	18.90	19.00	19.10	0.744	0.748	0.752
D1	----	17.60	----	----	0.693	----
E1	----	17.60	----	----	0.693	----
e	----	0.80	----	----	0.031	----
b	0.35	0.40	0.45	0.014	0.016	0.018
aaa		0.15			0.006	
bbb		0.20			0.008	
ddd		0.15			0.006	
eee		0.15			0.006	
fff		0.08			0.003	
MD/ME	23/23					

Fig.2-6 RK3228B BGA316 Package Dimension

2.4 Ball Map

2.4.1 BGA316 Ball Map

	1	2	3	4	5	6	7	8	9	10
A	DDR_CS N0	DDR_A4	NP	DDR_A1	DDR_A15	NP	DDR_DQ 3	DDR_DQS0	NP	DDR_DQ 16
B	DDR_CL K	DDR_ODT0	DDR_CK E	DDR_A12	DDR_A14	DDR_CSN1	DDR_DM 0	DDR_DQS0 _N	DDR_DQ 18	DDR_DQ 4
C	NP	DDR_CLK_ N	VSS47	DDR_A10	DDR_A11	NP	VSS1	DDR_DQ7	NP	VSS2
D	DDR_A0	DDR_A3	DDR_BA2	NP	DDR_WE N	NP	DDR_BA0	DDR_A8	NP	DDR_DQ 5
E	DDR_A9	DDR_A2	DDR_RA SN	DDR_A7	DDR_A5	NP	DDR_CA SN	DDR_BA1	NP	DDR_DQ 20
F	NP	DDR_DQ10	NP	NP	NP	DDR_RESE TN	DDR_A6	DDR_DQ1	NP	DDR_DQ 22
G	DDR_A13	DDR_ODT1	VSS3	DDR_DQ 26	DDR_DQ 9	DDR_DQ8	CVDD1	DDR_VDD5	DDR_VD D6	CVDD6
H	DDR_DQ S1	DDR_DQS1 _N	DDR_DQ 12	DDR_DM 1	DDR_DQ 28	DDR_DQ11	DDR_VD D4	VSS8	VSS9	VSS10
J	NP	DDR_DQ13	NP	NP	NP	NP	DDR_VD D3	VSS16	VSS17	VSS18
K	DDR_DQ 15	DDR_DQ14	VSS4	DDR_DQ 24	DDR_DQ 27	DDR_DQ29	CVDD2	VSS14	VSS22	VSS23

11	12	13	14	15	16	17	18	19	20	
DDR_DQ_S2	NP	DDR_DQ23	DDR_DQ0	NP	NC6	CODEC_VCM	NP	GPIO0_D1/UART2_CTSN	GPIO0_D6/SDMMC1_PWR/PWM1	A
DDR_DQ_S2_N	DDR_R_DQ21	DDR_DQ6	VSS15	CODEC_AOR	NC7	CODEC_AOL	NC3	GPIO1_B4/SPI_CSN1/PWM2	GPIO0_A6/HDMI_SCL/I2C3_SCL	B
DDR_DQ17	NP	VSS7	NC8	NP	NC2	GPIO0_D0/UART2_RTSN/OTP	GPIO3_C6/DRIVE_VBUS	GPIO0_C4/HDMI_CEC	NP	C
DDR_DM2	NP	CODEC_AVDD_1V8	CODEC_AVSS	NP	NC4	GPIO0_A3/I2C1_SDA/SDMMC1_CMD	GPIO1_B7/SDMMC0_CMD	GPIO3_C4	GPIO0_A0/I2C0_SCL	D
DDR_DQ19	NP	GPIO0_B7/HDMI_HPDI	NC1	NP	NC5	GPIO0_A1/I2C0_SDA	GPIO1_A1/SDMMC1_D0	GPIO1_A2/SPI_DMMC1_D1/I2S0_SDIO1	GPIO1_A0/SDMMC1_CCLK	E
DDR_DQ2	NP	GPIO3_C5/PWM0	GPIO0_A7/HDMI_SDA/I2C3_SDA	NP	NP	NP	NP	GPIO0_A2/I2C1_SCL	NP	F
DDR_VD7	DDR_VDD8	VSS6	VCCIO4	GPIO1_A3	GPIO1_A4/SPI_DMMC1_D2/I2S0_SDIO2	GPIO1_A5/SPI_DMMC1_D3/I2S0_SDIO3	GPIO1_B3/UART1_RTSN/IR	GPIO1_B0/UART1_CTSN/32K_OUT	GPIO3_C7	G
VSS11	VSS12	VSS13	CVDD5	TEST	GPIO0_B4/I2S0_LRCK_TX	GPIO0_B0/I2S0_MCLK	GPIO1_B1/UART1_TX/UART2_TX	GPIO1_B2/UART1_RX/UART2_RX	GPIO1_C0/SDMMC0_CCLK	H
VSS19	VSS20	VSS21	CVDD4	NP	NP	NP	NP	GPIO0_B3/I2S0_LRCK_RX/SPI_TXD	NP	J
VSS39	VSS24	VSS25	VCCIO3	GPIO1_C3/SPI_DMMC0_D1/UART2_RX	GPIO1_C4/SPI_DMMC0_D2/JTAG_TCK	GPIO2_A4/FLASH_RDY/EMMC_CMD	GPIO3_D7/TEST_CLK/O/SPDIF	GPIO0_B6/I2S0_SDI/SPI_CSN0	GPIO0_B1/I2S0_SCLK/SPI_CLK	K

L	DDR_DQS3	DDR_DQS3_N	DDR_DM3	DDR_DQ25	DDR_DQ30	DDR_DQ31	DDR_VDD2	VSS26	VSS27	VSS28
M	NP	VSS5	NP	NP	NP	NP	DDR_VDD1	VSS33	VSS34	VSS35
N	XIN24M	XOUT24M	A/GPLL_DVDD_1V0	C/DPLL_DVDD_1V0	PLL_AVDD_1V8	VCCIO1	VSS40	VSS41	VSS42	VSS43
P	GPIO2_C2/GMAC_TXD1/TS_D1	GPIO2_C3/GMAC_TXD0/TS_D0	GPIO2_C5/I2C2_SCL/GMAC_RXD2/CARD_RD_RST	GPIO2_C7/GMAC_TXD3/CARD_IO	GPIO2_C6/GMAC_TXD2/CARD_DET	GPIO2_D0/GMAC_C0L/TS_D5	AVSS1	AVSS2	NC9	CVDD3
R	NP	GPIO2_C1/GMAC_RXD0/TS_D2	NP	NP	NP	NP	NC10	FEPHY_AVDD_1V0	NP	EFUSE
T	GPIO2_B7/GMAC_RXER/TS_D6	GPIO2_D1/GMAC_MDC/TS_D4	GPIO2_C0/GMAC_RXD1/TS_D3	GPIO2_C4/I2C2_SDA/GMAC_RXD3/CARD_RD_CLK	GPIO2_B1/GMAC_TXCLK/TS_VALID	NP	VDAC_AVDD_1V8	AVSS7	NP	USB_AVDD3
U	GPIO2_B3/GMAC_RXCLK/TS_CLK	GPIO2_B5/GMAC_TXEN/TS_D7	GPIO2_B4/GMAC_MDIO/TS_SYNC	GPIO2_B6/GMAC_CLK/MAC_LINK	GPIO2_B0/GMAC_RXDV/MAC_SPEED	NP	NC11	VDAC_IREF	NP	GPIO3_D1
V	NP	HDMI_AVDD_1V8	AVSS8	HDMI_AVDD_1V0	GPIO2_B2/GMAC_CRD/TS_FAIL	NP	VDAC_IOUT	FEPHY_EXTR	NP	USB_EXTR1
W	HDMI_TXCN	HDMI_TX0N	HDMI_EXTR	HDMI_TX1N	HDMI_TX2N	AVSS3	FEPHY_TXP	FEPHY_RXP	AVSS4	FEPHY_TESATP
Y	HDMI_TXCP	HDMI_TX0P	NP	HDMI_TX1P	HDMI_TX2P	NP	FEPHY_TXN	FEPHY_RXN	NP	FEPHY_AVDD_1V8

1 2 3 4 5 6 7 8 9 10

VSS2 9	VSS 30	VSS3 1	VSS32	GPIO2_A3/FL ASH_RDN/SP I_CSN1	GPIO2_A6/F LASH_CS0	GPIO0_C7/F LASH_CS1/ SPI_CLK	GPIO1_C2/S DMMC0_D0/ UART2_TX	GPIO1_A7/SD MMC0_WP	GPIO0_B5/I2 S0_SDO/SPI _RXD	L
VSS3 6	VSS 37	VSS3 8	AVDD5	NP	NP	NP	NP	GPIO1_C5/SD MMC0_D3/JT AG_TMS	NP	M
VSS4 4	VSS 45	VSS4 6	AVDD4	GPIO1_D6/FL ASH_D6/EM MC_D6	GPIO2_A0/F LASH_ALE/ SPI_RXD	GPIO2_A1/F LASH_CLE/ SPI_TXD	GPIO1_B6/S DMMC0_PW R	GPIO2_A7/FL ASH_DQS/EM MC_CLKO	NPOR	N
GPIO 3_D4	AVD D1	AVDD 2	AVDD3	GPIO0_C1/U ART0_RTSN/ CLK_OUT1	GPIO1_D0/F LASH_D0/E MMC_D0	GPIO1_D7/F LASH_D7/E MMC_D7	GPIO1_D4/F LASH_D4/EM MC_D4	GPIO1_C7/FL ASH_CS3/EM MC_RST	GPIO2_A2/F LASH_WRN/ SPI_CSN0	P
USB0 _ID	NP	GPIO3 _A5/S DMM C1_D 3	GPIO3_A 6/UART1 _RTSN	NP	NP	NP	NP	GPIO1_D5/FL ASH_D5/EMM C_D5	NP	R
USB_ DVDD _1V0	NP	GPIO3 _A4/S DMM C1_D 2	VCCIO2	NP	GPIO3_A7/ UART1_CT SN	GPIO0_D3/ PWM1/PCM _TX	GPIO2_D2/U ART0_TX	GPIO1_D2/FL ASH_D2/EMM C_D2	GPIO1_D3/F LASH_D3/E MMC_D3	T
USB0 _VBU S	NP	GPIO3 _B4/P CM_S YNC	GPIO3_C 1/DRIVE _VBUS	NP	GPIO3_B6/ UART1_TX	GPIO3_A0/S DMMC1_CL KO	GPIO0_D2/P WM0/PCM_R X	GPIO1_C6/FL ASH_CS2/EM MC_CMD	GPIO1_D1/F LASH_D1/E MMC_D1	U
USB_ EXTR 0	NP	GPIO3 _B7/C LK_O UT0	GPIO0_D 4/PWM2	NP	GPIO3_A3/S DMMC1_D1	GPIO3_A1/S DMMC1_CM D	GPIO3_B5/U ART1_RX	GPIO2_A5/FL ASH_WP/EM MC_PWR	NP	V
USB3 _DP	AVS S6	USB2 _DP	USB1_D P	AVSS5	USB0_DP	GPIO3_A2/S DMMC1_D0	GPIO3_D2/IR	GPIO1_C1/SD MMC0_DET	GPIO2_D5/U ART0_CTSN	W
USB3 _DM	NP	USB2 _DM	USB1_D M	NP	USB0_DM	GPIO2_D3/ UART0_RX	NP	GPIO3_D3/SP DIF	GPIO3_B3/P CM_CLK	Y

11 12 13 14 15 16 17 18 19 20

Fig.2-7 RK3228BBGA316Ball Map

2.4.2 BGA400 Ball Map

	1	2	3	4	5	6	7	8	9	10	11	12	13
A	VSS	VSS	DDR_CL K_N	DDR_A1 0	VSS	NP	DDR_A 1	NP	NP	VSS	DDR_D Q3	NP	VSS
B	VSS	DDR_CAS N	DDR_CL K	DDR_A1 4	DDR_A1 1	VSS	VSS	DDR_B A1	NP	DDR_A 15	DDR_D Q6	DDR_D Q5	DDR_D Q0
C	DDR_A0	DDR_WE N	DDR_RA SN	VSS	DDR_A8	DDR_A 6	DDR_A 4	DDR_A 12	NP	DDR_D M0	DDR_D Q4	VSS	DDR_D Q2
D	NP	DDR_A13	VSS	DDR_A9	VSS	VSS	VSS	DDR_C KE	VSS	DDR_D Q1	DDR_D Q7	VSS	DDR_D Q18
E	DDR_RES ETN	VSS	DDR_A2	VSS	DDR_O DT1	VSS	DDR_V DD	VSS	VSS	VSS	VSS	VSS	VSS
F	VSS	DDR_A7	DDR_A5	VSS	DDR_C SN1	DDR_V DD							
G	NP	NP	DDR_A3	DDR_B A0	VSS	DDR_V DD	DDR_V DD	NP	NP	NP	NP	NP	NP
H	NP	NP	VSS	DDR_B A2	VSS	DDR_V DD	NP						
J	DDR_CSN 0	VSS	DDR_OD T0	VSS	DDR_D Q8	DDR_V DD	NP	NP	CVDD	VSS	VSS	CVDD	VSS
K	NP	DDR_DQ1 1	DDR_DQ 10	DDR_D Q9	VSS	DDR_V DD	NP	NP	VSS	VSS	VSS	VSS	VSS
L	VSS	DDR_DM1	VSS	DDR_D Q12	DDR_D Q13	DDR_V DD	NP	NP	VSS	VSS	VSS	VSS	VSS
M	DDR_DQS 1	DDR_DQS 1_N	VSS	VSS	VSS	VSS	NP	NP	VSS	VSS	VSS	VSS	VSS

14	15	16	17	18	19	20	21	22	23	
DDR_DQS2	NP	DDR_DQ16	VSS	NP	CODEC_AOR	GPIO3_D1	NP	GPIO1_A3	VSS	A
DDR_DQS2_N	DDR_DQS0_N	VSS	DDR_DQ19	VSS	CODEC_AOL	CODEC_AVSS	GPIO1_B4/SPI_CSN1/PWM2	GPIO3_C5/PWM0	GPIO1_A2/SDM_MC1_D1/I2S0_S DIO1	B
VSS	DDR_DQS0	DDR_DQ17	DDR_DQ21	CODEC_VC M	CODEC_AVDD_1 V8	GPIO0_D6/SDMMC1_PWR/PWM1	GPIO0_A0/I2C0_SCL	GPIO3_C7	GPIO0_A1/I2C0_SDA	C
DDR_DQ22	VSS	DDR_DM2	VSS	GPIO3_D4	GPIO0_D0/UART2_RTSN/OTP	GPIO3_C4	GPIO1_A1/SDM_MC1_D0	GPIO0_A2/I2C1_SCL	NP	D
DDR_DQ20	VSS	DDR_DQ23	VSS	GPIO0_D1/UART2_CT SN	GPIO0_A3/I2C1_SDA/SDMMC1_C MD	GPIO1_A4/SDMMC1_D2/I2S0_SDI O2	GPIO1_A5/SDM_MC1_D3/I2S0_S DIO3	NP	NP	E
VSS	VSS	VSS	VSS	GPIO3_C6/DRIVE_VBUS	VSS	GPIO1_A0/SDMMC1_CLKO	GPIO1_B2/UART1_RX/UART2_RX	GPIO1_B1/UART1_TX/UART2_TX	NP	F
NP	NP	NP	NP	NP	VCCIO4	GPIO1_B0/UART1_CTSN/32K_OUT	GPIO0_B6/I2S0_SDI/SPI_CSN0	GPIO0_B4/I2S0_LRCK_TX	GPIO0_B5/I2S0_SDO/SPI_RXD	G
NP	NP	NP	NP	NP	GPIO1_B3/UART1_RTSN/IR	GPIO0_B3/I2S0_LRCK_RX/SPI_TX D	GPIO1_B7/SDM_MC0_CMD	GPIO1_C4/SDM_MC0_D2/JTAG_TCK	GPIO1_C5/SDM_MC0_D3/JTAG_TMS	H
VSS	VSS	VSS	NP	NP	GPIO0_B1/I2S0_SCLK/SPI_CLK	GPIO0_B0/I2S0_MCLK	GPIO1_C0/SDM_MC0_CLKO	NP	NP	J
VSS	VSS	VSS	NP	NP	NPOR	GPIO3_D7/TEST_CLKO/SPDIF	GPIO1_A7/SDM_MC0_WP	GPIO1_C2/SDM_MC0_D0/UART2_TX	GPIO1_C3/SDM_MC0_D1/UART2_RX	K
VSS	VSS	CVD D	NP	NP	TEST	GPIO0_C1/UART0_RTSN/CLK_OUT1	GPIO1_B6/SDM_MC0_PWR	GPIO2_A4/FLASH_H_RDY/EMMC_C MD	GPIO2_A6/FLASH_H_CS0	L
VSS	VSS	CVD D	NP	NP	GPIO2_A0/FLASH_H_ALE/SPI_RXD	GPIO2_A7/FLASH_DQS/EMMC_CLKO	GPIO2_A3/FLASH_H_RDN/SPI_CSN1	NP	NP	M

N	NP	DDR_DQS3	DDR_DQ S3_N	DDR_DQ1 4	DDR_DQ26	VSS	NP	NP	CVD D	VSS	VSS	VSS	VSS
P	DDR_DQ15	VSS	DDR_DQ2 8	VSS	DDR_DQ27	VSS	NP	NP	VSS	VSS	VSS	VSS	VSS
R	VSS	DDR_DQ29	DDR_DQ2 4	DDR_DQ3 0	DDR_DQ25	VCCIO1	NP	NP	VSS	VSS	VSS	VSS	VSS
T	NP	DDR_DM3	VSS	DDR_DQ3 1	VSS	A/GPLL_D VDD_1V0	NP	NP	VSS	VSS	VSS	CVD D	VSS
U	VSS	VSS	VSS	VSS	C/DPLL_D VDD_1V0	VSS	NP	NP	NP	NP	NP	NP	NP
V	XIN24M	XOUT24M	VSS	PLL_AVD D_1V8	VSS	VSS	NP	NP	NP	NP	NP	NP	NP
W	NP	NP	VSS	GPIO2_C3 /GMAC_T XD0/TS_D 0	GPIO2_B7/ GMAC_RX ER/TS_D6	GPIO2_B 3/GMAC_ RXCLK/T S_CLK	HDMI_EX TR	HDM I_AV DD_ 1V8	HDM I_AV DD_ 1V0	HDM I_AV DD_ 1V0	VDA C_A VDD _1V8	FEPH Y_AV DD_1 V0	FEPH Y_AV DD_1 V8
Y	NP	GPIO2_C6/G MAC_TXD2/C ARD_DET	GPIO2_C 2/GMAC_ TXD1/TS_ D1	GPIO2_C1 /GMAC_R XD0/TS_D 2	GPIO2_B5/ GMAC_TX EN/TS_D7	VSS	GPIO0_A 6/HDMI_ SCL/I2C3 _SCL	HDM I_TX VSS 0N	HDM I_TX VSS 2N	HDM I_TX VSS 2N	VDA C_A VDD _1V8	FEPH Y_TE ST_A TP	FEPH Y_TE ST_A TP
A A	GPIO2_C5/I2 C2_SCL/GMA C_RXD2/CAR D_RST	GPIO2_C4/I2 C2_SDA/GMA C_RXD3/CAR D_CLK	GPIO2_C 0/GMAC_ RXD1/TS_ D3	GPIO2_B1 /GMAC_T XCLK/TS_ VALID	GPIO2_B0/ GMAC_RX DV/MAC_S PEED	VSS	GPIO0_C 4/HDMI_ CEC	VSS	HDM I_TX 0P	HDM I_TX VSS 2P	HDM I_TX VSS 2P	VDA C_A VDD _1V8	FEPH Y_EX TRES
A B	GPIO2_C7/G MAC_TXD3/C ARD_IO	GPIO2_D1/G MAC_MDC/T S_D4	GPIO2_D 0/GMAC_ COL/TS_ D5	GPIO2_B2 /GMAC_C RS/TS_FA IL	NP	GPIO0_B 7/HDMI_H PD	NP	HDM I_TX CN	HDM I_TX 1N	HDM I_TX 1N	VDA C_IR EF	NP	NP
A C	VSS	GPIO2_B6/G MAC_CLK/MA C_LINK	GPIO2_B4 /GMAC_M DIO/TS_S YNC	NP	NP	GPIO0_A 7/HDMI_S DA/I2C3_ SDA	NP	HDM I_TX CP	HDM I_TX 1P	HDM I_TX 1P	VDA C_IO UT	NP	NP
	1	2	3	4	5	6	7	8	9	10	11	12	13

VSS	VSS	VSS	NP	NP	VCCIO3	GPIO1_C6/FLAS H_CS2/EMMC_C MD	GPIO2_A1/FLAS H_CLE/SPI_TXD	GPIO2_A2/FLAS H_WRN/SPI_CS N0	GPIO0_C7/FLA SH_CS1/SPI_C LK	N
VSS	VSS	AVDD	NP	NP	NP	GPIO2_D5/UART 0_CTSN	GPIO2_A5/FLAS H_WP/EMMC_P WR	NP	NP	P
VSS	AVDD	AVDD	AVDD	NP	NP	GPIO3_B3/PCM_ CLK	GPIO1_D2/FLAS H_D2/EMMC_D2	GPIO1_D1/FLAS H_D1/EMMC_D1	GPIO1_D0/FLA SH_D0/EMMC_ D0	R
AVDD	AVDD	AVDD	AVDD	NP	NP	GPIO1_D4/FLAS H_D4/EMMC_D4	GPIO1_D3/FLAS H_D3/EMMC_D3	NP	NP	T
NP	NP	NP	NP	NP	NP	GPIO1_C1/SDMM C0_DET	GPIO1_D7/FLAS H_D7/EMMC_D7	GPIO1_D5/FLAS H_D5/EMMC_D5	GPIO1_D6/FLA SH_D6/EMMC_ D6	U
NP	NP	NP	NP	NP	NP	GPIO1_C7/FLAS H_CS3/EMMC_R ST	GPIO3_D3/SPDI F	GPIO0_D3/PWM 1/PCM_TX	NP	V
USB_A VDD_1 V8	USB_D VDD_1 V0	EFUSE	VCCIO2	VSS	GPIO3_B5/ UART1_R X	GPIO3_A7/UART 1_CTSN	GPIO3_D2/IR	GPIO2_D3/UART 0_RX	GPIO2_D2/UAR T0_TX	W
USB0_I D	USB_E XTR1	USB_A VDD_3 V3	GPIO0_ D4/PW M2	GPIO3_C1/ DRIVE_VB US	GPIO3_B4/ PCM_SYN C	GPIO3_B6/UART 1_TX	GPIO3_A6/UART 1_RTSN	GPIO3_B7/CLK_ OUT0	GPIO0_D2/PW M0/PCM_RX	Y
VSS	VSS	USB_E XTR0	VSS	VSS	VSS	VSS	GPIO3_A5/SDM MC1_D3	GPIO3_A4/SDM MC1_D2	NP	A A
FEPHY _TXP	FEPHY _RXP	USB0_ VBUS	USB0_D P	USB1_DP	USB2_DP	USB3_DP	GPIO3_A3/SDM MC1_D1	GPIO3_A0/SDM MC1_CLKO	GPIO3_A1/SDM MC1_CMD	A B
FEPHY _TXN	FEPHY _RXN	NP	USB0_D M	USB1_DM	USB2_DM	USB3_DM	NP	GPIO3_A2/SDM MC1_D0	VSS	A C
14	15	16	17	18	19	20	21	22	23	

Fig.2-8 RK3228BBGA400Ball Map

2.5 Pin Number Order

2.5.1 BGA316 Pin Number Order

Table 2-1RK3228B BGA316 Pin Number Order Information

Pin number	pin name	Pin number	pin name
A1	DDR_CS0	L1	DDR_DQS3
A2	DDR_A4	L2	DDR_DQS3_N
A4	DDR_A1	L3	DDR_DM3
A5	DDR_A15	L4	DDR_DQ25
A7	DDR_DQ3	L5	DDR_DQ30
A8	DDR_DQS0	L6	DDR_DQ31

Pin number	pin name	Pin number	pin name
A10	DDR_DQ16	L7	DDR_VDD2
A11	DDR_DQS2	L8	VSS26
A13	DDR_DQ23	L9	VSS27
A14	DDR_DQ0	L10	VSS28
A16	NC6	L11	VSS29
A17	CODEC_VCM	L12	VSS30
A19	GPIO0_D1/UART2_CTSN	L13	VSS31
A20	GPIO0_D6/SDMMC1_PWR/PWM1	L14	VSS32
B1	DDR_CLK	L15	GPIO2_A3/FLASH_RDN/SPI_CSN1
B2	DDR_ODT0	L16	GPIO2_A6/FLASH_CS0
B3	DDR_CKE	L17	GPIO0_C7/FLASH_CS1/SPI_CLK
B4	DDR_A12	L18	GPIO1_C2/SDMMC0_D0/UART2_TX
B5	DDR_A14	L19	GPIO1_A7/SDMMC0_WP
B6	DDR_CSN1	L20	GPIO0_B5/I2S0_SDO/SPI_RXD
B7	DDR_DM0	M2	VSS5
B8	DDR_DQS0_N	M7	DDR_VDD1
B9	DDR_DQ18	M8	VSS33
B10	DDR_DQ4	M9	VSS34
B11	DDR_DQS2_N	M10	VSS35
B12	DDR_DQ21	M11	VSS36
B13	DDR_DQ6	M12	VSS37
B14	VSS15	M13	VSS38
B15	CODEC_AOR	M14	AVDD5
B16	NC7	M19	GPIO1_C5/SDMMC0_D3/JTAG_TMS
B17	CODEC_AOL	N1	XIN24M
B18	NC3	N2	XOUT24M
B19	GPIO1_B4/SPI_CSN1/PWM2	N3	A/GPLL_DVDD_1V0
B20	GPIO0_A6/HDMI_SCL/I2C3_SCL	N4	C/DPLL_DVDD_1V0
C2	DDR_CLK_N	N5	PLL_AVDD_1V8
C3	VSS47	N6	VCCIO1
C4	DDR_A10	N7	VSS40
C5	DDR_A11	N8	VSS41
C7	VSS1	N9	VSS42
C8	DDR_DQ7	N10	VSS43
C10	VSS	N11	VSS44
C11	DDR_DQ17	N12	VSS45
C13	VSS2	N13	VSS46
C14	NC8	N14	AVDD4
C16	NC2	N15	GPIO1_D6/FLASH_D6/EMMC_D6
C17	GPIO0_D0/UART2_RTSN/OTP	N16	GPIO2_A0/FLASH_ALE/SPI_RXD
C18	GPIO3_C6/DRIVE_VBUS	N17	GPIO2_A1/FLASH_CLE/SPI_TXD
C19	GPIO0_C4/HDMI_CEC	N18	GPIO1_B6/SDMMC0_PWR
D1	DDR_A0	N19	GPIO2_A7/FLASH_DQS/EMMC_CLKO

Pin number	pin name	Pin number	pin name
D2	DDR_A3	N20	NPOR
D3	DDR_BA2	P1	GPIO2_C2/GMAC_TXD1/TS_D1
D5	DDR_WEN	P2	GPIO2_C3/GMAC_TXD0/TS_D0
D7	DDR_BA0	P3	GPIO2_C5/I2C2_SCL/GMAC_RXD2/CARD_RST
D8	DDR_A8	P4	GPIO2_C7/GMAC_TXD3/CARD_IO
D10	DDR_DQ5	P5	GPIO2_C6/GMAC_TXD2/CARD_DET
D11	DDR_DM2	P6	GPIO2_D0/GMAC_COL/TS_D5
D13	CODEC_AVDD_1V8	P7	AVSS1
D14	CODEC_AVSS	P8	AVSS2
D16	NC4	P9	NC9
D17	GPIO0_A3/I2C1_SDA/SDMMC1_CMD	P10	CVDD3
D18	GPIO1_B7/SDMMC0_CMD	P11	GPIO3_D4
D19	GPIO3_C4	P12	AVDD1
D20	GPIO0_A0/I2C0_SCL	P13	AVDD2
E1	DDR_A9	P14	AVDD3
E2	DDR_A2	P15	GPIO0_C1/UART0_RTSN/CLK_OUT1
E3	DDR_RASN	P16	GPIO1_D0/FLASH_D0/EMMC_D0
E4	DDR_A7	P17	GPIO1_D7/FLASH_D7/EMMC_D7
E5	DDR_A5	P18	GPIO1_D4/FLASH_D4/EMMC_D4
E7	DDR_CASN	P19	GPIO1_C7/FLASH_CS3/EMMC_RST
E8	DDR_BA1	P20	GPIO2_A2/FLASH_WRN/SPI_CSN0
E10	DDR_DQ20	R2	GPIO2_C1/GMAC_RXD0/TS_D2
E11	DDR_DQ19	R7	NC10
E13	GPIO0_B7/HDMI_HPD	R8	FEPHY_AVDD_1V0
E14	NC1	R10	EFUSE
E16	NC5	R11	USB0_ID
E17	GPIO0_A1/I2C0_SDA	R13	GPIO3_A5/SDMMC1_D3
E18	GPIO1_A1/SDMMC1_D0	R14	GPIO3_A6/UART1_RTSN
E19	GPIO1_A2/SDMMC1_D1/I2S0_SDIO1	R19	GPIO1_D5/FLASH_D5/EMMC_D5
E20	GPIO1_A0/SDMMC1_CLKO	T1	GPIO2_B7/GMAC_RXER/TS_D6
F2	DDR_DQ10	T2	GPIO2_D1/GMAC_MDC/TS_D4
F6	DDR_RESETN	T3	GPIO2_C0/GMAC_RXD1/TS_D3
F7	DDR_A6	T4	GPIO2_C4/I2C2_SDA/GMAC_RXD3/CARD_CLK
F8	DDR_DQ1	T5	GPIO2_B1/GMAC_TXCLK/TS_VALID
F10	DDR_DQ22	T7	VDAC_AVDD_1V8
F11	DDR_DQ2	T8	AVSS7
F13	GPIO3_C5/PWM0	T10	USB_AVDD_3V3
F14	GPIO0_A7/HDMI_SDA/I2C3_SDA	T11	USB_DVDD_1V0
F19	GPIO0_A2/I2C1_SCL	T13	GPIO3_A4/SDMMC1_D2
G1	DDR_A13	T14	VCCIO2
G2	DDR_ODT1	T16	GPIO3_A7/UART1_CTSN
G3	VSS3	T17	GPIO0_D3/PWM1/PCM_TX
G4	DDR_DQ26	T18	GPIO2_D2/UART0_TX

Pin number	pin name	Pin number	pin name
G5	DDR_DQ9	T19	GPIO1_D2/FLASH_D2/EMMC_D2
G6	DDR_DQ8	T20	GPIO1_D3/FLASH_D3/EMMC_D3
G7	CVDD1	U1	GPIO2_B3/GMAC_RXCLK/TS_CLK
G8	DDR_VDD5	U2	GPIO2_B5/GMAC_TXEN/TS_D7
G9	DDR_VDD6	U3	GPIO2_B4/GMAC_MDIO/TS_SYNC
G10	CVDD6	U4	GPIO2_B6/GMAC_CLK/MAC_LINK
G11	DDR_VDD7	U5	GPIO2_B0/GMAC_RXDV/MAC_SPEED
G12	DDR_VDD8	U7	NC11
G13	VSS6	U8	VDAC_IREF
G14	VCCIO4	U10	GPIO3_D1
G15	GPIO1_A3	U11	USB0_VBUS
G16	GPIO1_A4/SDMMC1_D2/I2S0_SDIO2	U13	GPIO3_B4/PCM_SYNC
G17	GPIO1_A5/SDMMC1_D3/I2S0_SDIO3	U14	GPIO3_C1/DRIVE_VBUS
G18	GPIO1_B3/UART1_RTSN/IR	U16	GPIO3_B6/UART1_TX
G19	GPIO1_B0/UART1_CTSN/32K_OUT	U17	GPIO3_A0/SDMMC1_CLKO
G20	GPIO3_C7	U18	GPIO0_D2/PWM0/PCM_RX
H1	DDR_DQS1	U19	GPIO1_C6/FLASH_CS2/EMMC_CMD
H2	DDR_DQS1_N	U20	GPIO1_D1/FLASH_D1/EMMC_D1
H3	DDR_DQ12	V2	HDMI_AVDD_1V8
H4	DDR_DM1	V3	AVSS8
H5	DDR_DQ28	V4	HDMI_AVDD_1V0
H6	DDR_DQ11	V5	GPIO2_B2/GMAC_CRIS/TS_FAIL
H7	DDR_VDD4	V7	VDAC_IOUT
H8	VSS8	V8	FEPHY_EXTRES
H9	VSS9	V10	USB_EXTR1
H10	VSS10	V11	USB_EXTR0
H11	VSS11	V13	GPIO3_B7/CLK_OUT0
H12	VSS12	V14	GPIO0_D4/PWM2
H13	VSS13	V16	GPIO3_A3/SDMMC1_D1
H14	CVDD5	V17	GPIO3_A1/SDMMC1_CMD
H15	TEST	V18	GPIO3_B5/UART1_RX
H16	GPIO0_B4/I2S0_LRCK_TX	V19	GPIO2_A5/FLASH_WP/EMMC_PWR
H17	GPIO0_B0/I2S0_MCLK	W1	HDMI_TXCN
H18	GPIO1_B1/UART1_TX/UART2_TX	W2	HDMI_TX0N
H19	GPIO1_B2/UART1_RX/UART2_RX	W3	HDMI_EXTR
H20	GPIO1_C0/SDMMC0_CLKO	W4	HDMI_TX1N
J2	DDR_DQ13	W5	HDMI_TX2N
J7	DDR_VDD3	W6	AVSS3
J8	VSS16	W7	FEPHY_TXP
J9	VSS17	W8	FEPHY_RXP
J10	VSS18	W9	AVSS4
J11	VSS19	W10	FEPHY_TEST_ATP
J12	VSS20	W11	USB3_DP

Pin number	pin name	Pin number	pin name
J13	VSS21	W12	AVSS6
J14	CVDD4	W13	USB2_DP
J19	GPI00_B3/I2S0_LRCK_RX/SPI_TXD	W14	USB1_DP
K1	DDR_DQ15	W15	AVSS5
K2	DDR_DQ14	W16	USB0_DP
K3	VSS4	W17	GPIO3_A2/SDMMC1_D0
K4	DDR_DQ24	W18	GPIO3_D2/IR
K5	DDR_DQ27	W19	GPIO1_C1/SDMMC0_DET
K6	DDR_DQ29	W20	GPIO2_D5/UART0_CTSN
K7	CVDD2	Y1	HDMI_TXCP
K8	VSS14	Y2	HDMI_TX0P
K9	VSS22	Y4	HDMI_TX1P
K10	VSS23	Y5	HDMI_TX2P
K11	VSS39	Y7	FEPHY_TXN
K12	VSS24	Y8	FEPHY_RXN
K13	VSS25	Y10	FEPHY_AVDD_1V8
K14	VCCIO3	Y11	USB3_DM
K15	GPIO1_C3/SDMMC0_D1/UART2_RX	Y13	USB2_DM
K16	GPIO1_C4/SDMMC0_D2/JTAG_TCK	Y14	USB1_DM
K17	GPIO2_A4/FLASH_RDY/EMMC_CMD	Y16	USB0_DM
K18	GPIO3_D7/TEST_CLKO/SPDIF	Y17	GPIO2_D3/UART0_RX
K19	GPI00_B6/I2S0_SDI/SPI_CSN0	Y19	GPIO3_D3/SPDIF
K20	GPI00_B1/I2S0_SCLK/SPI_CLK	Y20	GPIO3_B3/PCM_CLK

2.5.2 BGA400 Pin Number Order

Table 2-2 RK3228B BGA400 Pin Number Order Information

Pin num	Netname	Pin num	Netname
A1	VSS	M12	VSS
A2	VSS	M13	VSS
A3	DDR_CLK_N	M14	VSS
A4	DDR_A10	M15	VSS
A5	VSS	M16	CVDD
A6	NP	M17	NP
A7	DDR_A1	M18	NP
A8	NP	M19	GPIO2_A0/FLASH_ALE/SPI_RXD
A9	NP	M20	GPIO2_A7/FLASH_DQS/EMMC_CLKO
A10	VSS	M21	GPIO2_A3/FLASH_RDN/SPI_CSN1
A11	DDR_DQ3	M22	NP
A12	NP	M23	NP
A13	VSS	N1	NP
A14	DDR_DQS2	N2	DDR_DQS3
A15	NP	N3	DDR_DQS3_N
A16	DDR_DQ16	N4	DDR_DQ14

Pin num	Netname	Pin num	Netname
A17	VSS	N5	DDR_DQ26
A18	NP	N6	VSS
A19	CODEC_AOR	N7	NP
A20	GPIO3_D1	N8	NP
A21	NP	N9	CVDD
A22	GPIO1_A3	N10	VSS
A23	VSS	N11	VSS
B1	VSS	N12	VSS
B2	DDR_CASN	N13	VSS
B3	DDR_CLK	N14	VSS
B4	DDR_A14	N15	VSS
B5	DDR_A11	N16	VSS
B6	VSS	N17	NP
B7	VSS	N18	NP
B8	DDR_BA1	N19	VCCIO3
B9	NP	N20	GPIO1_C6/FLASH_CS2/EMMC_CMD
B10	DDR_A15	N21	GPIO2_A1/FLASH_CLE/SPI_TXD
B11	DDR_DQ6	N22	GPIO2_A2/FLASH_WRN/SPI_CSN0
B12	DDR_DQ5	N23	GPIO0_C7/FLASH_CS1/SPI_CLK
B13	DDR_DQ0	P1	DDR_DQ15
B14	DDR_DQS2_N	P2	VSS
B15	DDR_DQS0_N	P3	DDR_DQ28
B16	VSS	P4	VSS
B17	DDR_DQ19	P5	DDR_DQ27
B18	VSS	P6	VSS
B19	CODEC_AOL	P7	NP
B20	CODEC_AVSS	P8	NP
B21	GPIO1_B4/SPI_CSN1/PWM2	P9	VSS
B22	GPIO3_C5/PWM0	P10	VSS
B23	GPIO1_A2/SDMMC1_D1/I2S0_SDIO1	P11	VSS
C1	DDR_A0	P12	VSS
C2	DDR_WEN	P13	VSS
C3	DDR_RASN	P14	VSS
C4	VSS	P15	VSS
C5	DDR_A8	P16	AVDD
C6	DDR_A6	P17	NP
C7	DDR_A4	P18	NP
C8	DDR_A12	P19	NP
C9	NP	P20	GPIO2_D5/UART0_CTSN
C10	DDR_DM0	P21	GPIO2_A5/FLASH_WP/EMMC_PWR
C11	DDR_DQ4	P22	NP
C12	VSS	P23	NP
C13	DDR_DQ2	R1	VSS
C14	VSS	R2	DDR_DQ29

Pin num	Netname	Pin num	Netname
C15	DDR_DQS0	R3	DDR_DQ24
C16	DDR_DQ17	R4	DDR_DQ30
C17	DDR_DQ21	R5	DDR_DQ25
C18	CODEC_VCM	R6	VCCIO1
C19	CODEC_AVDD_1V8	R7	NP
C20	GPIO0_D6/SDMMC1_PWR/PWM1	R8	NP
C21	GPIO0_A0/I2C0_SCL	R9	VSS
C22	GPIO3_C7	R10	VSS
C23	GPIO0_A1/I2C0_SDA	R11	VSS
D1	NP	R12	VSS
D2	DDR_A13	R13	VSS
D3	VSS	R14	VSS
D4	DDR_A9	R15	AVDD
D5	VSS	R16	AVDD
D6	VSS	R17	AVDD
D7	VSS	R18	NP
D8	DDR_CKE	R19	NP
D9	VSS	R20	GPIO3_B3/PCM_CLK
D10	DDR_DQ1	R21	GPIO1_D2/FLASH_D2/EMMC_D2
D11	DDR_DQ7	R22	GPIO1_D1/FLASH_D1/EMMC_D1
D12	VSS	R23	GPIO1_D0/FLASH_D0/EMMC_D0
D13	DDR_DQ18	T1	NP
D14	DDR_DQ22	T2	DDR_DM3
D15	VSS	T3	VSS
D16	DDR_DM2	T4	DDR_DQ31
D17	VSS	T5	VSS
D18	GPIO3_D4	T6	A/GPLL_DVDD_1V0
D19	GPIO0_D0/UART2_RTSN/OTP	T7	NP
D20	GPIO3_C4	T8	NP
D21	GPIO1_A1/SDMMC1_D0	T9	VSS
D22	GPIO0_A2/I2C1_SCL	T10	VSS
D23	NP	T11	VSS
E1	DDR_RESETN	T12	CVDD
E2	VSS	T13	VSS
E3	DDR_A2	T14	AVDD
E4	VSS	T15	AVDD
E5	DDR_ODT1	T16	AVDD
E6	VSS	T17	AVDD
E7	DDR_VDD	T18	NP
E8	VSS	T19	NP
E9	VSS	T20	GPIO1_D4/FLASH_D4/EMMC_D4
E10	VSS	T21	GPIO1_D3/FLASH_D3/EMMC_D3
E11	VSS	T22	NP
E12	VSS	T23	NP

Pin num	Netname	Pin num	Netname
E13	VSS	U1	VSS
E14	DDR_DQ20	U2	VSS
E15	VSS	U3	VSS
E16	DDR_DQ23	U4	VSS
E17	VSS	U5	C/DPLL_DVDD_1V0
E18	GPIO0_D1/UART2_CTSN	U6	VSS
E19	GPIO0_A3/I2C1_SDA/SDMMC1_CMD	U7	NP
E20	GPIO1_A4/SDMMC1_D2/I2S0_SDIO2	U8	NP
E21	GPIO1_A5/SDMMC1_D3/I2S0_SDIO3	U9	NP
E22	NP	U10	NP
E23	NP	U11	NP
F1	VSS	U12	NP
F2	DDR_A7	U13	NP
F3	DDR_A5	U14	NP
F4	VSS	U15	NP
F5	DDR_CSN1	U16	NP
F6	DDR_VDD	U17	NP
F7	DDR_VDD	U18	NP
F8	DDR_VDD	U19	NP
F9	DDR_VDD	U20	GPIO1_C1/SDMMC0_DET
F10	DDR_VDD	U21	GPIO1_D7/FLASH_D7/EMMC_D7
F11	DDR_VDD	U22	GPIO1_D5/FLASH_D5/EMMC_D5
F12	DDR_VDD	U23	GPIO1_D6/FLASH_D6/EMMC_D6
F13	DDR_VDD	V1	XIN24M
F14	VSS	V2	XOUT24M
F15	VSS	V3	VSS
F16	VSS	V4	PLL_AVDD_1V8
F17	VSS	V5	VSS
F18	GPIO3_C6/DRIVE_VBUS	V6	VSS
F19	VSS	V7	NP
F20	GPIO1_A0/SDMMC1_CLKO	V8	NP
F21	GPIO1_B2/UART1_RX/UART2_RX	V9	NP
F22	GPIO1_B1/UART1_TX/UART2_TX	V10	NP
F23	NP	V11	NP
G1	NP	V12	NP
G2	NP	V13	NP
G3	DDR_A3	V14	NP
G4	DDR_BA0	V15	NP
G5	VSS	V16	NP
G6	DDR_VDD	V17	NP
G7	DDR_VDD	V18	NP
G8	NP	V19	NP
G9	NP	V20	GPIO1_C7/FLASH_CS3/EMMC_RST
G10	NP	V21	GPIO3_D3/SPDIF

Pin num	Netname	Pin num	Netname
G11	NP	V22	GPIO0_D3/PWM1/PCM_TX
G12	NP	V23	NP
G13	NP	W1	NP
G14	NP	W2	NP
G15	NP	W3	VSS
G16	NP	W4	GPIO2_C3/GMAC_TXD0/TS_D0
G17	NP	W5	GPIO2_B7/GMAC_RXER/TS_D6
G18	NP	W6	GPIO2_B3/GMAC_RXCLK/TS_CLK
G19	VCCIO4	W7	HDMI_EXTR
G20	GPIO1_B0/UART1_CTSN/32K_OUT	W8	HDMI_AVDD_1V8
G21	GPIO0_B6/I2S0_SDI/SPI_CSN0	W9	HDMI_AVDD_1V0
G22	GPIO0_B4/I2S0_LRCK_TX	W10	HDMI_AVDD_1V0
G23	GPIO0_B5/I2S0_SDO/SPI_RXD	W11	VDAC_AVDD_1V8
H1	NP	W12	FEPHY_AVDD_1V0
H2	NP	W13	FEPHY_AVDD_1V8
H3	VSS	W14	USB_AVDD_1V8
H4	DDR_BA2	W15	USB_DVDD_1V0
H5	VSS	W16	EFUSE
H6	DDR_VDD	W17	VCCIO2
H7	NP	W18	VSS
H8	NP	W19	GPIO3_B5/UART1_RX
H9	NP	W20	GPIO3_A7/UART1_CTSN
H10	NP	W21	GPIO3_D2/IR
H11	NP	W22	GPIO2_D3/UART0_RX
H12	NP	W23	GPIO2_D2/UART0_TX
H13	NP	Y1	NP
H14	NP	Y2	GPIO2_C6/GMAC_TXD2/CARD_DET
H15	NP	Y3	GPIO2_C2/GMAC_TXD1/TS_D1
H16	NP	Y4	GPIO2_C1/GMAC_RXD0/TS_D2
H17	NP	Y5	GPIO2_B5/GMAC_TXEN/TS_D7
H18	NP	Y6	VSS
H19	GPIO1_B3/UART1_RTSN/IR	Y7	GPIO0_A6/HDMI_SCL/I2C3_SCL
H20	GPIO0_B3/I2S0_LRCK_RX/SPI_TXD	Y8	VSS
H21	GPIO1_B7/SDMMC0_CMD	Y9	HDMI_TX0N
H22	GPIO1_C4/SDMMC0_D2/JTAG_TCK	Y10	VSS
H23	GPIO1_C5/SDMMC0_D3/JTAG_TMS	Y11	HDMI_TX2N
J1	DDR_CSN0	Y12	VSS
J2	VSS	Y13	FEPHY_TEST_ATP
J3	DDR_ODT0	Y14	USB0_ID
J4	VSS	Y15	USB_EXTR1
J5	DDR_DQ8	Y16	USB_AVDD_3V3
J6	DDR_VDD	Y17	GPIO0_D4/PWM2
J7	NP	Y18	GPIO3_C1/DRIVE_VBUS
J8	NP	Y19	GPIO3_B4/PCM_SYNC

Pin num	Netname	Pin num	Netname
J9	CVDD	Y20	GPIO3_B6/UART1_TX
J10	VSS	Y21	GPIO3_A6/UART1_RTSN
J11	VSS	Y22	GPIO3_B7/CLK_OUT0
J12	CVDD	Y23	GPIO0_D2/PWM0/PCM_RX
J13	VSS	AA1	GPIO2_C5/I2C2_SCL/GMAC_RXD2/CARD_RST
J14	VSS	AA2	GPIO2_C4/I2C2_SDA/GMAC_RXD3/CARD_CLK
J15	VSS	AA3	GPIO2_C0/GMAC_RXD1/TS_D3
J16	VSS	AA4	GPIO2_B1/GMAC_TXCLK/TS_VALID
J17	NP	AA5	GPIO2_B0/GMAC_RXDV/MAC_SPEED
J18	NP	AA6	VSS
J19	GPIO0_B1/I2S0_SCLK/SPI_CLK	AA7	GPIO0_C4/HDMI_CEC
J20	GPIO0_B0/I2S0_MCLK	AA8	VSS
J21	GPIO1_C0/SDMMC0_CLKO	AA9	HDMI_TX0P
J22	NP	AA10	VSS
J23	NP	AA11	HDMI_TX2P
K1	NP	AA12	VSS
K2	DDR_DQ11	AA13	FEPHY_EXTRES
K3	DDR_DQ10	AA14	VSS
K4	DDR_DQ9	AA15	VSS
K5	VSS	AA16	USB_EXTR0
K6	DDR_VDD	AA17	VSS
K7	NP	AA18	VSS
K8	NP	AA19	VSS
K9	VSS	AA20	VSS
K10	VSS	AA21	GPIO3_A5/SDMMC1_D3
K11	VSS	AA22	GPIO3_A4/SDMMC1_D2
K12	VSS	AA23	NP
K13	VSS	AB1	GPIO2_C7/GMAC_TXD3/CARD_IO
K14	VSS	AB2	GPIO2_D1/GMAC_MDC/TS_D4
K15	VSS	AB3	GPIO2_D0/GMAC_COL/TS_D5
K16	VSS	AB4	GPIO2_B2/GMAC_CRS/TS_FAIL
K17	NP	AB5	NP
K18	NP	AB6	GPIO0_B7/HDMI_HPD
K19	NPOR	AB7	NP
K20	GPIO3_D7/TEST_CLKO/SPDIF	AB8	HDMI_TXCN
K21	GPIO1_A7/SDMMC0_WP	AB9	NP
K22	GPIO1_C2/SDMMC0_D0/UART2_TX	AB10	HDMI_TX1N
K23	GPIO1_C3/SDMMC0_D1/UART2_RX	AB11	NP
L1	VSS	AB12	VDAC_IREF
L2	DDR_DM1	AB13	NP
L3	VSS	AB14	FEPHY_TXP
L4	DDR_DQ12	AB15	FEPHY_RXP
L5	DDR_DQ13	AB16	USB0_VBUS
L6	DDR_VDD	AB17	USB0_DP

Pin num	Netname	Pin num	Netname
L7	NP	AB18	USB1_DP
L8	NP	AB19	USB2_DP
L9	VSS	AB20	USB3_DP
L10	VSS	AB21	GPIO3_A3/SDMMC1_D1
L11	VSS	AB22	GPIO3_A0/SDMMC1_CLKO
L12	VSS	AB23	GPIO3_A1/SDMMC1_CMD
L13	VSS	AC1	VSS
L14	VSS	AC2	GPIO2_B6/GMAC_CLK/MAC_LINK
L15	VSS	AC3	GPIO2_B4/GMAC_MDIO/TS_SYNC
L16	CVDD	AC4	NP
L17	NP	AC5	NP
L18	NP	AC6	GPIO0_A7/HDMI_SDA/I2C3_SDA
L19	TEST	AC7	NP
L20	GPIO0_C1/UART0_RTSN/CLK_OUT1	AC8	HDMI_TXCP
L21	GPIO1_B6/SDMMC0_PWR	AC9	NP
L22	GPIO2_A4/FLASH_RDY/EMMC_CMD	AC10	HDMI_TX1P
L23	GPIO2_A6/FLASH_CS0	AC11	NP
M1	DDR_DQS1	AC12	VDAC_IOUT
M2	DDR_DQS1_N	AC13	NP
M3	VSS	AC14	FEPHY_TXN
M4	VSS	AC15	FEPHY_RXN
M5	VSS	AC16	NP
M6	VSS	AC17	USB0_DM
M7	NP	AC18	USB1_DM
M8	NP	AC19	USB2_DM
M9	VSS	AC20	USB3_DM
M10	VSS	AC21	NP
M11	VSS	AC22	GPIO3_A2/SDMMC1_D0
		AC23	VSS

2.6 RK3228B Power/Ground IO Description

Table 2-3 RK3228B Power/Ground IO information for BGA316

Group	Ball#	Descriptions
GND	B14, C3,C7,C10,C13, G3,G13, H8,H9,H10,H11,H12,H13, J8,J9,J10,J11,J12,J13, K3,K8,K9,K10,K11,K12,K13, L8,L9,L10,L11,L12,L13,L14 M2,M8,M9,M10,M11,M12,M13, N7,N8,N9,N10,N11,N12,N13	Internal Core Ground, Digital IO Ground,
AVSS	P7,P8,	Analog IO Ground

Group	Ball#	Descriptions
	V3, W6,W9,W12,W15	
AVDD	P12,P13,P14,N14,M14	ARM Core Power
CVDD	G7,K7,P10,J14,H14,G10	GPU,Logic Power
VCCIO1	N6	VCCIO1 PowerDomain Power
VCCIO2	T14	VCCIO2 PowerDomain Power
VCCIO3	K14	VCCIO3 PowerDomain Power
VCCIO4	G14	VCCIO4 PowerDomain Power
DDR_VDD	H7,J7,L7,M7,G12,G11,G9,G8	DDR PHY Power
A/GPLL_DVDD_1V0	N3	ARM PLL General PLL Analog Power
C/DPLL_DVDD_1V0	N4	Codec PLL DDR PLL Analog Power
PLL_AVDD_1V8	N5	PLL IO Power
USB_DVDD_1V0	T11	USB OTG2.0/Host2.0 Digital Power
USB_AVDD_3V3	T10	USB OTG2.0/Host2.0 Analog Power
CODEC_AVDD_1V8	D13	Audio Codec Analog Power
CODEC_AVSS	D14	Audio Codec Analog Ground
HDMI_AVDD_1V0	V4	HDMI PHY Analog Power
HDMI_AVDD_1V8	V2	HDMI PHY Analog Power
FEPHY_AVDD_1V0	R8	FEPHYLogic Analog Power
FEPHY_AVDD_1V8	Y10	FEPHY Analog Power
VDAC_AVDD_1V8	T7	VDAC Analog Power
AVSS	T8	VDAC Analog Ground

2.7 RK3228B Function IO Description

Table 2-4 RK3228B function IO description

Pad#	Ball #	func1	func2	func3	Pad Type [®]	Drive Strength [®]	Pull	Reset State [®]
GPIO0_A0/I2C0_SCL	D20	i2c0_scl			I/O	4mA	up	I
GPIO0_A1/I2C0_SDA	E17	i2c0_sda			I/O	4mA	up	I
GPIO0_A2/I2C1_SCL	F19	i2c1_scl			I/O	4mA	up	I
GPIO0_A3/I2C1_SDA/SDMMC1_CMD	D17	i2c1_sda	sdio_cmd		I/O	4mA	up	I
GPIO0_A6/HDMI_SCL/I2C3_SCL	B20	i2c3_scl	hdmi_ddcscl		I/O	4mA	up	I
GPIO0_A7/HDMI_SDA/I2C3_SDA	F14	i2c3_sda	hdmi_ddcsda		I/O	4mA	up	I
GPIO0_B0/I2S0_MCLK	H17	i2s_mclk			I/O	4mA	up	I
GPIO0_B1/I2S0_SCLK/SPI_CLK	K20	i2s_sclk	spi_clk		I/O	4mA	up	I
GPIO0_B3/I2S0_LRCK_RX/SPI_TXD	J19	i2s_lrckrx	spi_txd		I/O	4mA	up	I
GPIO0_B4/I2S0_LRCK_TX	H16	i2s_lrcktx			I/O	4mA	up	I
GPIO0_B5/I2S0_SDO/SPI_RXD	L20	i2s_sdo	spi_rxd		I/O	4mA	up	I
GPIO0_B6/I2S0_SDI/SPI_CSN0	K19	i2s_sdi	spi_csn0		I/O	4mA	up	I
GPIO0_C1/UART0_RTSN/CLK_OUT1	P15	uart0_rtsn	clk_out1		I/O	4mA	up	I
GPIO0_C4/HDMI_CEC	C19	hdmi_cecsda			I/O	4mA	up	I
GPIO0_C7/FLASH_CS1/SPI_CLK	L17	nand_cs1	spi1_clk		I/O	8mA	up	I
GPIO0_D0/UART2_RTSN/OTP	C17	uart2_rtsn	tsadc_shut		I/O	4mA	up	I
GPIO0_D1/UART2_CTSN	A19	uart2_ctsn			I/O	4mA	up	I
GPIO0_D2/PWM0/PCM_RX	U18	pwm_0	pcm_rx		I/O	4mA	down	I
GPIO0_D3/PWM1/PCM_TX	T17	pwm_1	pcm_tx		I/O	4mA	down	I
GPIO0_D4/PWM2	V14	pwm_2			I/O	8mA	up	I
GPIO0_D6/SDMMC1_PWR/PWM1	A20	sdio_pwren	pwm1_1		I/O	4mA	down	I
GPIO1_A0/SDMMC1_CLKO	E20	sdio_clkout			I/O	4mA	down	I
GPIO1_A1/SDMMC1_D0	E18	sdio_d0			I/O	4mA	up	I
GPIO1_A2/SDMMC1_D1/I2S0_SDIO1	E19	sdio_d1	i2s_sdio1		I/O	4mA	up	I
GPIO1_A3	G15				I/O	4mA	down	I
GPIO1_A4/SDMMC1_D2/I2S0_SDIO2	G16	sdio_d2	i2s_sdio2		I/O	4mA	up	I
GPIO1_A5/SDMMC1_D3/I2S0_SDIO3	G17	sdio_d3	i2s_sdio3		I/O	4mA	up	I
GPIO1_A7/SDMMC0_WP	L19	sdmmc_wrprt			I/O	4mA	down	I
GPIO1_B0/UART1_CTSN/32K_OUT	G19	uart1_ctsn	clkout_32k		I/O	4mA	up	I
GPIO1_B1/UART1_TX/UART2_TX	H18	uart1_sout	uart21_sout		I/O	4mA	up	I
GPIO1_B2/UART1_RX/UART2_RX	H19	uart1_sin	uart21_sin		I/O	4mA	up	I
GPIO1_B3/UART1_RTSN/IR	G18	uart1_rtsn	pwm1_ir		I/O	4mA	up	I
GPIO1_B4/SPI_CSN1/PWM2	B19	spi_csn1	pwm1_2		I/O	4mA	up	I
GPIO1_B6/SDMMC0_PWR	N18	sdmmc_pwren			I/O	4mA	down	I
GPIO1_B7/SDMMC0_CMD	D18	sdmmc_cmd			I/O	8mA	up	I
GPIO1_C0/SDMMC0_CLKO	H20	sdmmc_clkout			I/O	8mA	down	I
GPIO1_C1/SDMMC0_DET	W19	sdmmc_detn			I/O	4mA	up	I
GPIO1_C2/SDMMC0_D0/UART2_TX	L18	sdmmc_d0	uart2_sout		I/O	8mA	up	I
GPIO1_C3/SDMMC0_D1/UART2_RX	K15	sdmmc_d1	uart2_sin		I/O	8mA	up	I
GPIO1_C4/SDMMC0_D2/JTAG_TCK	K16	sdmmc_d2	jtag_tck		I/O	8mA	up	I

Pad#	Ball #	func1	func2	func3	Pad Type®	Drive Strength®	Pull	Reset State®
GPIO1_C5/SDMMC0_D3/JTAG_TMS	M19	sdmmc_d3	jtag_tms		I/O	8mA	up	I
GPIO1_C6/FLASH_CS2/EMMC_CMD	U19	nand_cs2	emmc_cmd		I/O	8mA	up	I
GPIO1_C7/FLASH_CS3/EMMC_RST	P19	nand_cs3	emmc_rstnou t		I/O	8mA	up	I
GPIO1_D0/FLASH_D0/EMMC_D0	P16	nand_d0	emmc_d0		I/O	8mA	up	I
GPIO1_D1/FLASH_D1/EMMC_D1	U20	nand_d1	emmc_d1		I/O	8mA	up	I
GPIO1_D2/FLASH_D2/EMMC_D2	T19	nand_d2	emmc_d2		I/O	8mA	up	I
GPIO1_D3/FLASH_D3/EMMC_D3	T20	nand_d3	emmc_d3		I/O	8mA	up	I
GPIO1_D4/FLASH_D4/EMMC_D4	P18	nand_d4	emmc_d4		I/O	8mA	up	I
GPIO1_D5/FLASH_D5/EMMC_D5	R19	nand_d5	emmc_d5		I/O	8mA	up	I
GPIO1_D6/FLASH_D6/EMMC_D6	N15	nand_d6	emmc_d6		I/O	8mA	up	I
GPIO1_D7/FLASH_D7/EMMC_D7	P17	nand_d7	emmc_d7		I/O	8mA	up	I
GPIO2_A0/FLASH_ALE/SPI_RXD	N16	nand_ale	spi1_rxd		I/O	8mA	down	I
GPIO2_A1/FLASH_CLE/SPI_TXD	N17	nand_cle	spi1_txd		I/O	8mA	down	I
GPIO2_A2/FLASH_WRN/SPI_CSN0	P20	nand_wrn	spi1_csn0		I/O	8mA	up	I
GPIO2_A3/FLASH_RDN/SPI_CSN1	L15	nand_rdn	spi1_csn1		I/O	8mA	up	I
GPIO2_A4/FLASH_RDY/EMMC_CMD	K17	nand_rdy	emmc1_cmd		I/O	8mA	up	I
GPIO2_A5/FLASH_WP/EMMC_PWR	V19	nand_wp	emmc_pwren		I/O	8mA	down	I
GPIO2_A6/FLASH_CS0	L16	nand_cs0			I/O	8mA	up	I
GPIO2_A7/FLASH_DQS/EMMC_CLKO	N19	nand_dqs	emmc_clkout		I/O	8mA	up	I
GPIO2_B0/GMAC_RXDV/MAC_SPEED	U5	gmac_rxdv	mac_speed		I/O	8mA	down	I
GPIO2_B1/GMAC_TXCLK/TS_VALID	T5	gmac_txclk	ts_vaild		I/O	8mA	down	I
GPIO2_B2/GMAC_CRCS/TS_FAIL	V5	gmac_crs	ts_fail		I/O	8mA	down	I
GPIO2_B3/GMAC_RXCLK/TS_CLK	U1	gmac_rxclk	ts_clk		I/O	8mA	down	I
GPIO2_B4/GMAC_MDIO/TS_SYNC	U3	gmac_mdio	ts_sync		I/O	8mA	down	I
GPIO2_B5/GMAC_TXEN/TS_D7	U2	gmac_txen	ts_d7		I/O	8mA	down	I
GPIO2_B6/GMAC_CLK/MAC_LINK	U4	gmac_clk	mac_link		I/O	8mA	down	I
GPIO2_B7/GMAC_RXER/TS_D6	T1	gmac_rxer	ts_d6		I/O	8mA	down	I
GPIO2_C0/GMAC_RXD1/TS_D3	T3	gmac_rxd1	ts_d3		I/O	8mA	down	I
GPIO2_C1/GMAC_RXD0/TS_D2	R2	gmac_rxd0	ts_d2		I/O	8mA	down	I
GPIO2_C2/GMAC_TXD1/TS_D1	P1	gmac_txd1	ts_d1		I/O	8mA	down	I
GPIO2_C3/GMAC_TXD0/TS_D0	P2	gmac_txd0	ts_d0		I/O	8mA	down	I
GPIO2_C4/I2C2_SDA/GMAC_RXD3/CARD_CLK	T4	i2c2_sda	gmac_rxd3	card_clk	I/O	8mA	down	I
GPIO2_C5/I2C2_SCL/GMAC_RXD2/CARD_RST	P3	i2c2_scl	gmac_rxd2	card_rst	I/O	8mA	down	I
GPIO2_C6/GMAC_TXD2/CARD_DET	P5	gmac_txd2	card_det		I/O	8mA	down	I
GPIO2_C7/GMAC_TXD3/CARD_IO	P4	gmac_txd3	card_io		I/O	8mA	down	I
GPIO2_D0/GMAC_COL/TS_D5	P6	gmac_col	ts_d5		I/O	8mA	down	I
GPIO2_D1/GMAC_MDC/TS_D4	T2	gmac_mdc	ts_d4		I/O	8mA	down	I
GPIO2_D2/UART0_TX	T18	uart0_sout			I/O	4mA	down	I
GPIO2_D3/UART0_RX	Y17	uart0_sin			I/O	4mA	down	I
GPIO2_D5/UART0_CTSN	W20	uart0_ctsn			I/O	4mA	down	I

Pad#	Ball #	func1	func2	func3	Pad Type®	Drive Strength®	Pull	Reset State®
GPIO3_B3/PCM_CLK	Y20	pcm_clk			I/O	4mA	down	I
GPIO3_C1/DRIVE_VBUS	U14	drive_vbus			I/O	8mA	down	I
GPIO3_C4	D19				I/O	4mA	down	I
GPIO3_C5/PWM0	F13	pwm1_0			I/O	4mA	down	I
GPIO3_C6/DRIVE_VBUS	C18	drive_vbus1			I/O	4mA	down	I
GPIO3_C7	G20				I/O	4mA	up	I
GPIO3_D1	U10				I/O	4mA	up	I
GPIO3_D2/IR	W18	pwm_ir			I/O	4mA	up	I
GPIO3_D3/SPDIF	Y19	spdif_tx			I/O	4mA	up	I
GPIO3_D4	P11				I/O	4mA	down	I
GPIO3_D7/TEST_CLKO/SPDIF	K18	testclk_out1	spdif1_tx		I/O	4mA	down	I
GPIO3_A0/SDMMC1_CLKO	U17	sdio1_clk			I/O	8mA	down	I
GPIO3_A1/SDMMC1_CMD	V17	sdio1_cmd			I/O	8mA	up	I
GPIO3_A2/SDMMC1_D0	W17	sdio1_d0			I/O	8mA	up	I
GPIO3_A3/SDMMC1_D1	V16	sdio1_d1			I/O	8mA	up	I
GPIO3_A4/SDMMC1_D2	T13	sdio1_d2			I/O	8mA	up	I
GPIO3_A5/SDMMC1_D3	R13	sdio1_d3			I/O	8mA	up	I
GPIO3_A6/UART1_RTSN	R14	uart11_rtsn			I/O	4mA	down	I
GPIO3_A7/UART1_CTSN	T16	uart11_ctsn			I/O	4mA	down	I
GPIO3_B4/PCM_SYNC	U13	pcm_sync			I/O	4mA	down	I
GPIO3_B5/UART1_RX	V18	uart11_sin			I/O	4mA	down	I
GPIO3_B6/UART1_TX	U16	uart11_sout			I/O	4mA	down	I
GPIO3_B7/CLK_OUT0	V13	clk_out0			I/O	8mA	down	I
NPOR	N20				I	4mA	up	I
TEST	H15				I	4mA	down	I
XIN24M	N1				I			I
XOUT24M	N2				O			I
GPIO0_B7/HDMI_HPD	E13	hdmi_hpd			I/O	4mA	down	I
HDMI_EXTR	W3				A			
HDMI_TXCN	W1				A			
HDMI_TX0N	W2				A			
HDMI_TX2N	W5				A			
HDMI_TXCP	Y1				A			
HDMI_TX0P	Y2				A			
HDMI_TX2P	Y5				A			
HDMI_TX1N	W4				A			
HDMI_TX1P	Y4				A			
MAC_TXN	Y7				A			
MAC_TXP	W7				A			
MAC_RXP	W8				A			
MAC_RXN	Y8				A			
MAC_TEST_ATP	W10				A			
MAC_EXTRES	V8				A			

Pad#	Ball #	func1	func2	func3	Pad Type®	Drive Strength®	Pull	Reset State®
CODEC_AOR	B15				A			
CODEC_AOL	B17				A			
CODEC_VCM	A17				A			
USB2_DP	W13				A			
USB2_DM	Y13				A			
USB_EXTR1	V10				A			
USB3_DP	W11				A			
USB3_DM	Y11				A			
USB0_DP	W16				A			
USB0_DM	Y16				A			
USB_EXTR0	V11				A			
USB1_DP	W14				A			
USB1_DM	Y14				A			
VDAC_IREF	U8				A			
VDAC_IOUT	V7				A			
DDR_DQ30	L5				A			
DDR_DQ1	F8				A			
DDR_A6	F7				A			
DDR_A14	B5				A			
DDR_DQ8	G6				A			
DDR_DQ10	F2				A			
DDR_DQ11	H6				A			
DDR_DQS1_N	H2				A			
DDR_DQ25	L4				A			
DDR_DM1	H4				A			
DDR_DQ31	L6				A			
DDR_DQ3	A7				A			
DDR_DQ26	G4				A			
DDR_DQ28	H5				A			
DDR_DQ29	K6				A			
DDR_DQ24	K4				A			
DDR_DQS3	L1				A			
DDR_DQ27	K5				A			
DDR_DM3	L3				A			
DDR_DQ9	G5				A			
DDR_A15	A5				A			
DDR_BA1	E8				A			
DDR_A12	B4				A			
DDR_A11	C5				A			
DDR_A1	A4				A			
DDR_RESETN	F6				A			
DDR_DQS3_N	L2				A			
DDR_DQ12	H3				A			

Pad#	Ball #	func1	func2	func3	Pad Type®	Drive Strength®	Pull	Reset State®
DDR_A4	A2				A			
DDR_ODT0	B2				A			
DDR_BA0	D7				A			
DDR_ODT1	G2				A			
DDR_A9	E1				A			
DDR_A3	D2				A			
DDR_A8	D8				A			
DDR_A0	D1				A			
DDR_DQ18	B9				A			
DDR_CSN1	B6				A			
DDR_RASN	E3				A			
DDR_A13	G1				A			
DDR_BA2	D3				A			
DDR_A2	E2				A			
DDR_A10	C4				A			
DDR_DQS0	A8				A			
DDR_DQS0_N	B8				A			
DDR_DQ19	E11				A			
DDR_DM2	D11				A			
DDR_DQ16	A10				A			
DDR_DQ17	C11				A			
DDR_DQ22	F10				A			
DDR_DQ20	E10				A			
DDR_DQ4	B10				A			
DDR_DQS2	A11				A			
DDR_DQ0	A14				A			
DDR_DQ2	F11				A			
DDR_DQ5	D10				A			
DDR_DQ6	B13				A			
DDR_DQ21	B12				A			
DDR_DQ23	A13				A			
DDR_DM0	B7				A			
DDR_DQ15	K1				A			
DDR_DQS2_N	B11				A			
DDR_DQ7	C8				A			
DDR_CSN0	A1				A			
DDR_CKE	B3				A			
DDR_CASN	E7				A			
DDR_CLK	B1				A			
DDR_A7	E4				A			
DDR_DQS1	H1				A			
DDR_DQ14	K2				A			
DDR_DQ13	J2				A			

Pad#	Ball #	func1	func2	func3	Pad Type ^①	Drive Strength ^②	Pull	Reset State ^③
DDR_A5	E5				A			
DDR_CLK_N	C2				A			
DDR_WEN	D5				A			

Notes:

^①: Pad types: I = input, O = output, I/O = input/output (bidirectional)

AP = Analog Power, AG = Analog Ground

DP = Digital Power, DG = Digital Ground

A = Analog

^②: Output Drive Unit is mA, only Digital IO has drive value;

^③: Reset state: I = input without any pull resistor, O = output without any pull resistor;

2.8 IO Pin Name Description

This sub-chapter will focus on the detailed function description of every pins based on different interface.

Table 2-5 RK3228B IO function description list

Interface	Pin Name	Direction	Description
Misc	XIN24M	I	Clock input of 24MHz crystal
	XOUT24M	O	Clock output of 24MHz crystal
	NPOR	I	Chip hardware reset

Interface	Pin Name	Direction	Description
SWJ-DP	jtag_tck	I	JTAG interface clock input/SWD interface clock input
	jtag_tms	I/O	JTAG interface TMS input/SWD interface data out

Interface	Pin Name	Direction	Description
SD/MMC Host Controller	sdmmc0_clkout	O	sdmmc card clock
	sdmmc0_cmd	I/O	sdmmc card command output and reponse input
	sdmmc0_data <i>i</i> (<i>i</i> =0~3)	I/O	sdmmc card data input and output
	sdmmc0_detect_n	I	sdmmc card detect signal, 0 represents presence of card

Interface	Pin Name	Direction	Description
SDIO Host Controller	sdio_clkout	O	sdio card clock
	sdio_cmd	I/O	sdio card command output and reponse input
	sdio_data <i>i</i> (<i>i</i> =0~3)	I/O	sdio card data input and output

Interface	Pin Name	Direction	Description
eMMC Interface	emmc_clkout	O	emmc card clock
	emmc_cmd	I/O	emmc card command output and reponse input
	emmc_data <i>i</i> (<i>i</i> =0~7)	I/O	emmc card data input and output

Interface	Pin Name	Direction	Description
DMC	CLK	O	Active-high clock signal to the memory device.
	CLK_N	O	Active-low clock signal to the memory device.
	CKE	O	Active-high clock enable signal to the memory device
	CSNi (i=0,1)	O	Active-low chip select signal to the memory device. AThere are two chip select.
	RASN	O	Active-low row address strobe to the memory device.
	CASN	O	Active-low column address strobe to the memory device.
	WEN	O	Active-low write enable strobe to the memory device.
	BAi(i=0,1,2)	O	Bank address signal to the memory device.
	Ai(i=0~15)	O	Address signal to the memory device.
	DQi(i=0~31)	I/O	Bidirectional data line to the memory device.
	DQS0 DQS1 DQS2 DQS3	I/O	Active-high bidirectional data strobes to the memory device.
	DQS0_N DQS1_N DQS2_N DQS3_N	I/O	Active-low bidirectional data strobes to the memory device.
	DMi(i=0~3)	O	Active-low data mask signal to the memory device.
	ODTi(i=0,1)	O	On-Die Termination output signal for two chip select.
	RESETN	O	DDR3 reset signal to the memory device

Interface	Pin Name	Direction	Description
NandC	flash_wp	O	Flash write-protected signal
	flash_ale	O	Flash address latch enable signal
	flash_cle	O	Flash command latch enable signal
	flash_wrn	O	Flash write enable and clock signal
	flash_rdn	O	Flash read enable and write/read signal
	flash_datai(i=0~7)	I/O	Flash data inputs/outputs signal
	flash_rdy	I	Flash ready/busy signal
	flash_csn0	O	Flash chip enable signal for chip0

Interface	Pin Name	Direction	Description
SIM Card	sc_clk	O	Smart card clock output
	sc_rst	O	Smart card reset output
	sc_io	I/O	Smart card data
	sc_detect	O	Smart card detect input

Interface	Pin Name	Direction	Description
TSP Interface	ts_clk	I/O	TSI reference clock
	ts_data <i>i</i> (<i>i</i> =0~7)	I	TSI data(<i>i</i> =0~7)
	ts_sync	I	TSI synchronizer signal
	ts_valid	I	TSI valid signal
	ts_fail	I	TSI fail signal

Interface	Pin Name	Direction	Description
I2S/PCM Controller	i2s_clk	O	I2S/PCM clock source
	i2s_sclk	I/O	I2S/PCM serial clock
	i2s_lrckrx	I/O	I2S/PCM left & right channel signal for receiving serial data, synchronous left & right channel in I2S mode and the beginning of a group of left & right channels in PCM mode
	i2s_lrcktx	I/O	I2S/PCM left & right channel signal for transmitting serial data, synchronous left & right channel in I2S mode and the beginning of a group of left & right channels in PCM mode
	i2s_sdi	I	I2S/PCM serial data input
	i2s_sdio <i>i</i> (<i>i</i> =0~3)	O	I2S/PCM serial data output

Interface	Pin Name	Direction	Description
SPDIF transmitter	spdif_tx	O	SPDIFbiphase data ouput

Interface	Pin Name	Direction	Description
SPI Controller	spi_clk	I/O	SPI serial clock
	spi_csn(<i>i</i> =0,1)	I/O	SPI chip select signal,low active
	spi_txd	O	SPI serial data output
	spi_rxd	I	SPI serial data input

Interface	Pin Name	Direction	Description
PWM	pwm3	O	Pulse Width Modulation output
	pwm2	O	Pulse Width Modulation output
	pwm1	O	Pulse Width Modulation output
	pwm0	O	Pulse Width Modulation output

Interface	Pin Name	Direction	Description
I2C	i2c0_sda	I/O	I2C0 data
	i2c0_scl	I/O	I2C0 clock
	i2c1_sda	I/O	I2C1 data
	i2c1_scl	I/O	I2C1 clock
	i2c2_sda	I/O	I2C2 data
	i2c2_scl	I/O	I2C2 clock
	i2c3_sda	I/O	I2C3 data
	i2c3_scl	I/O	I2C3 clock

Interface	Pin Name	Direction	Description
UART	uart0_sin	I	UART0 serial data input
	uart0_sout	O	UART0 serial data output
	uart0_ctsn	I	UART0 clear to send
	uart0_rtsn	O	UART0 request to send
	uart1_sin	I	UART1 serial data input
	uart1_sout	O	UART1 serial data output
	uart2_sin	I	UART2 serial data input
	uart2_sout	O	UART2 serial data output

Interface	Pin Name	Direction	Description
GMAC	mac_clk	I/O	RMII REC_CLK output or GMAC external clock input
	mac_mdc	O	GMACmanagement interface clock
	mac_mdio	I/O	GMAC management interface data
	mac_txdi(i=0~1)	O	GMAC TX data
	max_rxd(i=0~1)	I	GMAC RX data
	mac_txen	O	GMAC TX data enable
	mac_rxer	I	GMAC RX error signal
	mac_crs	I	PHY CRS signal

Interface	Pin Name	Direction	Description
EMAC	MAC_TXN	I/O	Transmit data - Negative
	MAC_TXP	I/O	Transmit data - Positive
	MAC_RXP	I/O	Receive data - Positive
	MAC_RXN	I/O	Receive data - Negative
	MAC_TEST_ATP	I/O	Analog test pin
	MAC_EXTRES	I/O	Connection to reference resistor

Interface	Pin Name	Direction	Description
USB OTG 2.0	USB0_DP	I/O	USB OTG 2.0 Data signal DP
	USB0_DM	I/O	USB OTG 2.0 Data signal DM

Interface	Pin Name	Direction	Description
USB Host 2.0	USB1DP	I/O	USB HOST 2.0 Data signal DP
	USB1DN	I/O	USB HOST 2.0 Data signal DM
	USB2DP	I/O	USB HOST 2.0 Data signal DP
	USB2DN	I/O	USB HOST 2.0 Data signal DM
	USB3DP	I/O	USB HOST 2.0 Data signal DP
	USB3DN	I/O	USB HOST 2.0 Data signal DM

Interface	Pin Name	Direction	Description
eFuse	EFUSE_VQPS	N/A	eFuse program and sense power

Interface	Pin Name	Direction	Description
HDMI	EXTR	O	Connect 2.0Kohm resistor to ground to generate

Interface	Pin Name	Direction	Description
			reference current
	HPD	I/O	HDMI hot plug detect signal
	TX0N	O	TMDS channel 0 negative data line
	TX0P	O	TMDS channel 0 positive data line
	TX1N	O	TMDS channel 1 negative data line
	TX1P	O	TMDS channel 1 positive data line
	TX2N	O	TMDS channel 2 negative data line
	TX2P	O	TMDS channel 2 positive data line
	TX3N	O	TMDS negative clock line
	TX3P	O	TMDS positive clock line



Interface	Pin Name	Direction	Description
Audio CODEC	CODEC_VCM	I	Reference voltage input
	CODEC_AOL	O	Left channel output
	CODEC_AOR	O	Right channel output

Interface	Pin Name	Direction	Description
Video DAC	VDAC_IREF	I/O	Reference current. Output current when using External Reference Resistor or Input Reference Current when using external current source
	VDAC_IOUT	O	Positive output

2.9 RK3228B IO Type

The following list shows IO type except DDR IO and all of Power/Ground IO.

Table 2-6 RK3228B IO Type List

Type	Diagram	Description	Pin Name
A		Analog IO Cell with IO voltage	EFUSE_VQPS
C		Crystal Oscillator with high enable	XIN24M/XOUT24M
D		Tri-state output pad with input, which pull-up/pull-down, slew rate and drive strength is configurable	Pad of digital GPIO

Chapter 3 Electrical Specification

3.1 Absolute Maximum Ratings

Table 3-1 RK3228B absolute maximum ratings

Parameters	Related Power Group	Max	Unit
DC supply voltage for Internal digital logic	AVDD, CVDD, USB_AVDD_1V0 DDRPLL_VDD_1V0	1.4	V
DC supply voltage for Digital GPIO (except for PLL, USB, DDR, HDMI IO)	VCCIO1 VCCIO2 VCCIO3 VCCIO4	3.6	V
DC supply voltage for DDR IO	DDR_VDD	1.65	V
DC supply voltage for digital part of PLL	C/DPLL_AVDD_1V0 A/GPLL_AVDD_1V0	1.1	V
DC supply voltage for Analog part of PLL	PLL_AVDD_1V8	1.98	V
DC supply voltage for Analog part of USB OTG/Host2.0	USB_AVDD_3V3	3.63	V
DC supply voltage for Analog part of Audio Codec	CODEC_AVDD_1V8	1.98	V
DC supply voltage for Analog part of VDAC	VDAC_AVDD_1V8	1.98	V
DC supply voltage for Analog part of HDMI	HDMI_AVDD_1V0 HDMI_AVDD_1V8	1.1 1.98	V
DC supply voltage for Analog part of MAC	MAC_AVDD_1V0 MAC_AVDD_1V8	1.1 1.98	V
Analog Input voltage for DP/DM/VBUS of USB OTG/Host2.0		5	V
Digital input voltage for input buffer of GPIO		3.6	V
Digital output voltage for output buffer of GPIO		3.6	V
Storage Temperature	Tstg	125	°C
Max Conjunction Temperature	Tj	125	°C

Absolute maximum ratings specify the values beyond which the device may be damaged permanently. Long-term exposure to absolute maximum ratings conditions may affect device reliability.

3.2 Recommended Operating Condition

Following table describes the recommended operating condition.

Table 3-2 RK3228B recommended operating condition

Parameters	Symbol	Min	Typ	Max	Units
Internal digital logic Power	AVDD, CVDD, USB_AVDD_1V0 DDRPLL_VDD_1V0	0.9	1.0	TBD	V
Digital GPIO	VCCIO1	3	3.3	3.6	V

Parameters	Symbol	Min	Typ	Max	Units
Power(3.3V/2.5V/1.8V)	VCCIO2	2.25	2.5	2.75	
	VCCIO3	1.62	1.8	1.98	
	VCCIO4				
DDR IO (DDR3 mode) Power	DDR_VDD	1.425	1.5	1.575	V
DDR IO (DDR3L mode) Power	DDR_VDD	1.283	1.35	1.417	V
DDR IO (LPDDR2/LPDDR3 mode) Power	DDR_VDD	1.14	1.2	1.3	V
PLL Digital Power	C/DPLL_AVDD_1V0 A/GPLL_AVDD_1V0	0.9	1.0	1.1	V
PLL Analog Power	PLL_AVDD_1V8	1.62	1.8	1.98	V
ACODEC Analog Power	CODEC_AVDD_1V8	1.62	1.8	1.98	V
VDAC Analog Power	VDAC_AVDD_1V8	1.62	1.8	1.98	V
USB OTG/Host2.0 Digital Power	USB_AVDD_1V0	0.9	1.0	1.1	V
USB OTG/Host2.0 Analog Power(3.3V)	USB_AVDD_3V3	3.069	3.3	3.63	V
HDMI Analog Power(1.0V)	HDMI_AVDD_1V0	0.9	1.0	1.1	V
HDMI Analog Power(1.8V)	HDMI_AVDD_1V8	1.62	1.8	1.98	V
FEPHY Analog Power(1.0V)	FEPHY_AVDD_1V0	0.9	1.0	1.1	V
FEPHY Analog Power(1.8V)	FEPHY_AVDD_1V8	1.62	1.8	1.98	V
PLL input clock frequency		N/A	24	N/A	MHz
Ambient Operating Temperature \varnothing		0	25	80	°C

Notes :[⊗] Symbol name is same as the pin name in the io descriptions

[⊗] with the reference software setup, the reference software will limit the chipset temperature about 80 °C

3.3 DC Characteristics

Table 3-3 RK3228B DC Characteristics

Parameters	Symbol	Min	Typ	Max	Units	
Digital GPIO @3.3V	Input Low Voltage	Vil	-0.3	0	3.3x0.3	V
	Input High Voltage	Vih	3.3x0.7	3.3	3.3+0.3	V
	Output Low Voltage	Vol	-0.3	NA	NA	V

Parameters		Symbol	Min	Typ	Max	Units	
	Output High Voltage	Voh	NA	NA	3.6	V	
	Threshold Point	Vtr+	1.53	1.46	1.43	V	
		Vtr-	1.19	1.12	1.05	V	
	Pullup Resistor	Rpu	33.7	58	101.5	Kohm	
	Pulldown Resistor	Rpd	34.2	60.1	109.3	Kohm	
Digital GPIO @1.8V	Input Low Voltage	Vil	-0.3	0	1.8x0.3	V	
	Input High Voltage	Vih	1.8x0.7	1.8	1.8 + 0.3	V	
	Output Low Voltage	Vol	-0.3	NA	NA	V	
	Output High Voltage	Voh	NA	NA	1.8+0.3	V	
	Threshold Point	Vtr+	1.23	1.12	1.03	V	
		Vtr-	0.91	0.82	0.73	V	
	Pullup Resistor	Rpu	35	62.9	120	Kohm	
	Pulldown Resistor	Rpd	35.1	61	113.9	Kohm	
DDR IO @DDR3 mode	Input High Voltage	Vih_dds	VREF + 0.10	NA	DDR_VDD+0.4	V	
	Input Low Voltage	Vil_dds	-0.4	NA	VREF - 0.10	V	
	Output High Voltage	Voh_dds	0.9xDDR_VDD	NA	N/A	V	
	Output Low Voltage	Vol_dds	N/A	NA	0.1*DDR_VDD	V	
	Input termination resistance(ODT) to VDDIO_DDRi/2 (i=0~6)	Rtt	100 54 36	120 60 40	140 66 44	Ohm	
DDR IO @LPDDR2/ LPDDR3 mode	Input High Voltage	Vih_dds	VREF + 0.13	NA	DDR_VDD	V	
	Input Low Voltage	Vil_dds	0	NA	VREF - 0.13	V	
	Output High Voltage	Voh_dds	NA	NA	0.9*DDR_VDD	V	
	Output Low Voltage	Vol_dds	0.1*DDR_VDD	NA	NA	V	
HDMI	Single-ended standby voltage	Voff	avddtmds±10			mV	
	Single-ended output swing voltage RT=50Ω	Vswing	400		600	mV	
		Vswing_data	400		600	mV	
		Vswing_clock	400		600	mV	
	Single-ended output high voltage	Vh	avddtmds-400			avddtmds+10	mV
		Vh_data	avddtmds-400			avddtmds+10	mV
		Vh_clock	avddtmds-400			avddtmds+10	mV
	Single-ended output low voltage	Vl	avddtmds-1000			avddtmds-400	mV
		Vl_data	avddtmds-1000			avddtmds-400	mV

Parameters		Symbol	Min	Typ	Max	Units
		Vl_clock	avddtmds-100 0		avddtmds-4 00	mV
	Differential source termination load	Rterm	75		150	Ω

3.4 Electrical Characteristics for General IO

Table 3-4 RK3228B Electrical Characteristics for Digital General IO

Parameters		Symbol	Test condition	Min	Typ	Max	Units
Digital GPIO @3.3V	Input leakage current	Ii	Vin = 3.3V or 0V	NA	NA	10	uA
	Tri-state output leakage current	Ioz	Vout = 3.3V or 0V	NA	NA	10	uA
	High level input current	Iih	Vin = 3.3V, pulldown disabled	NA	NA	10	uA
			Vin = 3.3V, pulldown enabled	NA	NA	106.4	uA
	Low level input current	Iil	Vin = 0V, pullup disabled	NA	NA	10	uA
			Vin = 0V, pullup enabled	NA	NA	107.8	uA
Digital GPIO @1.8V	Input leakage current	Ii	Vin = 1.8V or 0V	NA	NA	10	uA
	Tri-state output leakage current	Ioz	Vout = 1.8V or 0V	NA	NA	10	uA
	High level input current	Iih	Vin = 1.8V, pulldown disabled	NA	NA	10	uA
			Vin = 1.8V, pulldown enabled	NA	NA	61.3	uA
	Low level input current	Iil	Vin = 0V, pullup disabled	NA	NA	10	uA
			Vin = 0V, pullup enabled	NA	NA	61.4	uA

3.5 Electrical Characteristics for PLL

Table 3-5 RK3228B Electrical Characteristics for PLL

Parameters		Symbol	Test condition	Min	Typ	Max	Units
PLL	Input clock frequency(Int)	F _{in}	Fin = FREF @3.3V/1.1V	1		800	MHz
	Input clock frequency(Frac)	F _{in}	Fin = FREF @3.3V/1.1V	10		800	MHz
	VCO operating range	F _{vco}	Fvco = Fref * FBDIV @3.3V/1.1V	800		3200	MHz
	Output clock frequency	F _{out}	Fout = Fvco/POSTDIV @3.3V/1.1V	16		3200	MHz
	Lock time	T _{lt}	@ 3.3V/1.1V,		250	500	Input

Parameters	Symbol	Test condition	Min	Typ	Max	Units
		FREF=24M,REFDIV=1				clock cycles
VDDHV current consumption		Fvco = 1000MHz, @3.3V Current scale as (Fvco/1GHz) ^{1.5}		1.0	1.2	mA
VDD Current consumption		VDD =1.1V		1.3	1.56	uA/MHz
Power consumption (power-down mode)		PD=HIGH, @27 °C		13		uA

Notes :

REFDIV is the input divider value;
 FBDIV is the feedback divider value;
 POSTDIV is the output divider value

3.6 Electrical Characteristics for USB Interface

Table 3-6 RK3228B Electrical Characteristics for USB Interface

Parameters	Symbol	Test condition	Min	Typ	Max	Units
Transmitter						
High input level	VIH		NA	1.0	NA	V
Low input level	VIL		NA	0	NA	V
Output resistance	ROUT	Classic mode (Vout = 0 or 3.3V)	40.5	45	49.5	ohms
		HS mode (Vout = 0 to 800mV)	40.5	45	49.5	ohms
Output Capacitance	COUT	seen from D+ or D-			3	pF
Output Common Mode Voltage	VM	Classic (LS/FS) mode	1.45	1.65	1.85	V
		HS mode	0.175	0.2	0.225	V
Differential output signal high	VOH	Classic (LS/FS); Io=0mA	2.97	3.3	3.63	V
		Classic (LS/FS); Io=6mA	2.2	0.3	NA	V
		HS mode; Io=0mA	360	400	440	mV
Differential output signal low	VOL	Classic (LS/FS); Io=0mA	-0.33	0	0.33	V
		Classic (LS/FS); Io=6mA	NA	0.3	0.8	V
		HS mode; Io=0mA	-40	0	40	mV
Receiver						
Receiver sensitivity	RSENS	Classic mode		+ -250		mV

Parameters	Symbol	Test condition	Min	Typ	Max	Units
		HS mode		+ -25		mV
Receiver common mode	RCM	Classic mode	0.8	1.65	2.5	V
		HS mode (differential and squelch comparator)	0.1	0.2	0.3	V
		HS mode (disconnect comparator)	0.5	0.6	0.7	V
Input capacitance (seen at D+ or D-)			NA	NA	3	pF
Squelch threshold			100	112	150	mV
Disconnect threshold			570	590	625	mV
High output level	VOH		NA	3.3	NA	V
Low output level	VOL		NA	0	NA	V

3.7 Electrical Characteristics for DDR IO

Table 3-7 RK3228B Electrical Characteristics for DDR IO

Parameters		Symbol	Test condition	Min	Typ	Max	Units
DDR IO @DDR3 mode	Input leakage current, SSTL mode, unterminated		@ 1.5V , 125°C	NA	0		uA
DDR IO @DDR3L mode	Input leakage current		@ 1.35V , 125°C	NA	0	NA	nA
DDR IO @LPDDR2/LPDDR3 mode	Input leakage current		@ 1.2V , 125°C	NA	0	0.49	nA

3.8 Electrical Characteristics for eFuse

Table 3-8 RK3228B Electrical Characteristics for eFuse

	Parameters	Symbol	Test condition	Min	Typ	Max	Units
Active mode	VDD current in Read mode	Iread_vdd	nomal read	15	20	30	mA
	VDD current in PGM mode	Ipgm_vdd	STROBE high	0.5	1	2.5	mA
	VQPS current in PGM mode	Ipgm_vqps	STROBE high	5	10	15	mA
standby mode	VDD current in standby mode	Istandby_vdd	Standby	0.2	0.5	2	A

3.9 Electrical Characteristics for HDMI

Table 3-9 RK3228B Electrical Characteristics for HDMI

Parameters	Symbol	Test condition	Min	Typ	Max	Units
Trise and Tfall			<200			ps
Frequency Tolerance, max			-300 ~300			ppm
Clock duty cycle			40%		60%	
Power consumption		1080p		60		mA
Power consumption		2160p		100		mA

3.10 Electrical Characteristics for VDAC

Table 3-10 RK3228B Electrical Characteristics for VDAC

Parameters	Symbol	Test condition	Min	Typ	Max	Units
High voltage analog current consumption	I _{AVDD}	I _{fs} =34mA		39		mA
Digital current consumption	I _{VDD}	F _s =100MHz		0.1		mA
Current consumption in power down, analog	I _{AVDD}			10		uA
Current consumption in power down, digital	I _{VDD}			1		uA

3.11 Electrical Characteristics for TSADC

Table 3-11 RK3228B Electrical Characteristics for TSADC

Parameters	Symbol	Test condition	Min	Typ	Max	Units
Temperature Resolution				5		°C
Temperature Range			0		80	°C
Analog power	I _{AVDD}	F _s = 50KS/s		190		uA
Digital power	I _{VDD}	F _s = 50KS/s		10		uA
Clock Frequency	F _{clk}	F _{clk}			800	KHz
Power Down Current from Analog	I _{AVDD}	Power down		1		uA
Power Down Current from Digital	I _{VDD}	Power down		1		uA

Chapter 4 Thermal Management

4.1 Overview

For reliability and operability concerns, the absolute maximum junction temperature of RK3228B has to be below 125°C.

4.2 Package Thermal Characteristics

Table 4-1 provides the thermal resistance characteristics for the package used on RK3228B. The resulting simulation data for reference only, please prevail in kind test.

Table 4-1 RK3228B Thermal Resistance Characteristics

Package (TFBGA316)	Power(W)	θ_{JA} (°C/W)	θ_{JB} (°C/W)	θ_{JC} (°C/W)
RK3228B RK3228B-D	3.2	22.95	13.47	12.73
RK3228B2 RK3228B2-D	3.2	27.2	18.6	12.7

Note: The testing PCB is base on 4 layers, 14mmx 14mm, 1.9 mm Thickness, Ambient temperature is 25 ° C.